

(19) World Intellectual Property Organization
International Bureau



(43) International Publication Date
5 November 2009 (05.11.2009)

PCT

(10) International Publication Number
WO 2009/135132 A1

- (51) International Patent Classification:
H04B 10/155 (2006.01) G01V 8/00 (2006.01)
- (21) International Application Number:
PCT/US2009/042532
- (22) International Filing Date:
1 May 2009 (01.05.2009)
- (25) Filing Language: English
- (26) Publication Language: English
- (30) Priority Data:
61/049,488 1 May 2008 (01.05.2008) US
- (71) Applicant (for all designated States except US): **BATTELLE MEMORIAL INSTITUTE** [US/US]; 505 King Avenue, Columbus, OH 43201-2696 (US).
- (72) Inventor; and
- (75) Inventor/Applicant (for US only): **RIDGWAY, Richard, W.** [US/US]; 505 King Avenue, Columbus, OH 43201-2696 (US).
- (74) Agents: **BEYER, James, E.** et al.; Dinsmore & Shohl LLP, One South Main Street, One Dayton Centre, Suite 1300, Dayton, OH 45402-2023 (US).

- (81) Designated States (unless otherwise indicated, for every kind of national protection available): AE, AG, AL, AM, AO, AT, AU, AZ, BA, BB, BG, BH, BR, BW, BY, BZ, CA, CH, CN, CO, CR, CU, CZ, DE, DK, DM, DO, DZ, EC, EE, EG, ES, FI, GB, GD, GE, GH, GM, GT, HN, HR, HU, ID, IL, IN, IS, JP, KE, KG, KM, KN, KP, KR, KZ, LA, LC, LK, LR, LS, LT, LU, LY, MA, MD, ME, MG, MK, MN, MW, MX, MY, MZ, NA, NG, NI, NO, NZ, OM, PG, PH, PL, PT, RO, RS, RU, SC, SD, SE, SG, SK, SL, SM, ST, SV, SY, TJ, TM, TN, TR, TT, TZ, UA, UG, US, UZ, VC, VN, ZA, ZM, ZW.
- (84) Designated States (unless otherwise indicated, for every kind of regional protection available): ARIPO (BW, GH, GM, KE, LS, MW, MZ, NA, SD, SL, SZ, TZ, UG, ZM, ZW), Eurasian (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM), European (AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HR, HU, IE, IS, IT, LT, LU, LV, MC, MK, MT, NL, NO, PL, PT, RO, SE, SI, SK, TR), OAPI (BF, BJ, CF, CG, CI, CM, GA, GN, GQ, GW, ML, MR, NE, SN, TD, TG).

Published:

— with international search report (Art. 21(3))

(54) Title: SPECTRALLY EFFICIENT DIGITAL DATA TRANSMISSION UTILIZING PHASE ENCODED MMW




FIG. 1

(57) **Abstract:** A digital data transmission device is provided comprising optical waveguide architecture, a sideband generator, a modulation controller, an optical filter, a data mapping unit, and a phase controller. The optical waveguide architecture is configured to direct an optical signal through the sideband generator and the optical filter. The sideband generator comprises an electrooptic interferometer comprising first and second waveguide arms. The modulation controller is configured to generate an electrical drive signal to drive the sideband generator at a control voltage that is substantially larger than $V\pi$ to generate optical frequency sidebands about a carrier frequency of the optical signal. The optical filter is configured to discriminate between the optical frequency sidebands and the optical carrier frequency such that optical sidebands of interest can be directed through the optical waveguide architecture as an optical millimeter wave signal. The data mapping unit is configured to generate an encoded data signal representing a digital data input received by the data mapping unit. The phase controller is configured to alter the phase of the electrical drive signal in response to the encoded data signal generated by the data mapping unit. The sideband generator is configured such that encoded alterations in the phase of the electrical drive signal are manifested as encoded alterations in the phase of the optical millimeter wave signal, creating an encoded representation of the digital data input in the optical millimeter wave signal. Methods of transmitting digital data are also provided.



WO 2009/135132 A1

SPECTRALLY EFFICIENT DIGITAL DATA TRANSMISSION UTILIZING PHASE ENCODED MMW

The present disclosure relates to optical devices and, more specifically, to optical devices that are configured to generate high frequency optical signals that can be encoded with data and converted to an electrical data signal.

By way of illustration, not limitation, there is a growing interest in the generation
5 and modulation of high frequency signals. For example, the present inventors have contemplated that signals in the THz spectrum (0.1 to 10 THz) may find significant utility in imaging and wireless applications. For imaging, the THz spectrum may provide high resolution imaging through walls, cargo containers, and other visible barriers. It is contemplated that modulation onto these high frequency signals can provide improved
10 resolution and the ability to separate a desired target from clutter. For wireless data communications, it is contemplated that the THz spectrum may allow ultra high data transfer (10 Gb/s) for transmission of uncompressed high definition television channels. However, significant design challenges face those who endeavor to design systems for the generation and modulation of coherent THz and other high frequency signals.

15 For example, millimeter-wave carrier frequencies (30 GHz to 300 GHz) provide a promising approach for achieving high data rates. Commercial millimeter-wave systems operating at 70 GHz have demonstrated data links at rates of 1 Gb/s. These data rates are not as high as would be expected at this carrier frequency because millimeter-wave sources cannot be directly modulated and instead the modulation occurs at a lower
20 intermediate frequency. The data rate is limited to 10 percent on the intermediate frequency (typically 11 GHz) to about 1 Gb/s.

Optical approaches for generating and modulating millimeter-wave signals, such as those presented in published patent application US 2008/0199124 A1, carry out modulation on an optical carrier, which can easily handle data rates in excess of 10 Gb/s.
25 To date, these optical approaches have used on-off keying modulation schemes. However, on-off key modulation is not spectrally efficient and consumes a bandwidth of about 1 Hz for each bit/second of data rate. For example, 10 Gb/s wireless data rates for millimeter-wave carriers around 100 GHz typically occupy a bandwidth of 10 GHz.

-2-

The present disclosure relates to the use of an electrooptic modulator to provide phase modulation onto a millimeter-wave carrier in an effort to increase spectral efficiency of digital data transmission. The phase of the microwave drive signal driving an overdriven electrooptic modulator will influence the phase of the generated sidebands
5 formed on either side of an optical carrier signal. After removing the unwanted sidebands using an optical filter, the remaining optical signal will contain a phase-modulated millimeter-wave signal on the optical carrier. A high speed photodiode can be used to remove the optical carrier and leave the phase modulated millimeter-wave signal. Phase modulation techniques, such as quadrature phase shift keying, can be shown to be
10 spectrally efficient, with a spectral efficiency of 2, i.e., 1 Hz of bandwidth will contain 2 b/s of data. Higher order phase modulation can provide even more spectral efficiency.

In addition to controlling the phase of the millimeter-wave signal, the electrooptic modulator can control the amplitude of the millimeter-wave signal. If amplitude and phase can be controlled, then Quadrature Amplitude Modulation (QAM) can be realized,
15 which has even higher spectral efficiency. The present disclosure shows that a photonic approach to generating and modulating millimeter-waves can be used to control both the amplitude and phase of the millimeter wave. This will lead to the ability to provide high-order phase modulation and QAM, both of which are spectrally efficient. A spectrally efficient modulation scheme will consume less bandwidth than a standard on-off keying
20 modulation approach.

A typical rule of thumb suggests that a carrier frequency can employ 10 percent of its bandwidth for data. In other words, a 10 GHz carrier can be used to transmit data at 1 Gb/s and a 100 GHz carrier can be used to transmit data at 10 Gb/s. Spectral efficient coding allows more bits to fit within the allowable bandwidth. As an example,
25 quadrature-phase shift keying (QPSK), which has a spectral efficiency of 2 bits/second per hertz, can encode 20 Gb/s within the 10 GHz bandwidth. More efficient coding methods, such as quadrature amplitude modulation (QAM), can provide higher data rates within the same bandwidth.

In accordance with one embodiment of the present disclosure, a digital data
30 transmission device is provided comprising optical waveguide architecture, a sideband generator, a modulation controller, an optical filter, a data mapping unit, and a phase

-3-

controller. The optical waveguide architecture is configured to direct an optical signal through the sideband generator and the optical filter. The sideband generator comprises an electrooptic interferometer comprising first and second waveguide arms. The modulation controller is configured to generate an electrical drive signal to drive the sideband

5 generator at a control voltage that is substantially larger than V_{π} to generate optical frequency sidebands about a carrier frequency of the optical signal. The optical filter is configured to discriminate between the optical frequency sidebands and the optical carrier frequency such that optical sidebands of interest can be directed through the optical waveguide architecture as an optical millimeter wave signal. The data mapping unit is

10 configured to generate an encoded data signal representing a digital data input received by the data mapping unit. The phase controller is configured to alter the phase of the electrical drive signal in response to the encoded data signal generated by the data mapping unit. The sideband generator is configured such that encoded alterations in the phase of the electrical drive signal are manifested as encoded alterations in the phase of

15 the optical millimeter wave signal, creating an encoded representation of the digital data input in the optical millimeter wave signal.

In accordance with another embodiment of the present disclosure, a method of transmitting digital data is provided. According to the method, an optical signal is directed through a sideband generator comprising an electrooptic interferometer

20 comprising first and second waveguide arms. The sideband generator is driven with an electrical drive signal at a control voltage that is substantially larger than V_{π} to generate optical frequency sidebands about a carrier frequency of the optical signal. The optical frequency sidebands and the optical carrier frequency are discriminated to generate an optical millimeter wave signal. The phase of the electrical drive signal is altered in

25 response to an encoded data signal representing a digital data input such that encoded alterations in the phase of the electrical drive signal are manifested as encoded alterations in the phase of the optical millimeter wave signal, creating an encoded representation of the digital data input in the optical millimeter wave signal. The method may further comprise a step of altering the amplitude of the optical millimeter wave signal in further

30 response to the encoded data signal such that encoded alterations in the amplitude of the

optical millimeter wave signal create a further encoded representation of the digital data input in the optical millimeter wave signal.

The following detailed description of specific embodiments of the present disclosure can be best understood when read in conjunction with the following drawings, where like structure is indicated with like reference numerals and in which:

Fig. 1 is a schematic illustration of a digital data transmission device according to one embodiment of the present disclosure; and

Fig. 2 is a schematic illustration of a digital data transmission device according to another embodiment of the present disclosure.

Published United States Patent Application US 2008/0199124 (“Optical Device for Generating and Modulating THz and Other High Frequency Signals”) presents a detailed illustration of the manner in which an electrooptic interferometer can be configured to generate a series of optical frequency sidebands about a carrier frequency of an optical signal. In general, a modulation controller generates an electrical drive signal that drives the sideband generator at a control voltage that is substantially larger than V_π to generate the optical frequency sidebands. V_π represents the voltage at which a π phase shift is induced between respective arms of the interferometer. The reference also describes the manner in which an optical filter can be configured to direct optical sidebands of interest through an optical waveguide architecture as an optical millimeter wave signal that can be encoded to carry data.

As is noted above, the present disclosure relates to the use of a sideband generator similar to that described in the aforementioned published US patent application to impart phase modulation onto a millimeter-wave carrier in an effort to increase spectral efficiency of digital data transmission. To understand how phase modulation appears on the sidebands, the phase of the electrical drive signal ϕ_e can be tracked in the mathematical relationship of a modulated optical signal. Specifically, the optical signal output of a Mach-Zehnder Interferometer Modulator is given by:

$$E_I(t) = E_o \cos\left\{\frac{\phi_{DC}}{2} + \beta_i \sin[\omega_e t + \phi_e(t)]\right\} \cdot \cos[\omega_o t + \phi_o(t)] \quad (1)$$

-5-

where ϕ_{DC} is the constant phase shift due to the DC bias of the modulator, ω_o and $\phi_o(t)$ are associated with the optical frequency and ω_e and $\phi_e(t)$ are associated with the modulation frequency f_e (i.e. $\omega_e = 2\pi f_e$). The modulation index β_i is given by:

$$\beta_i = \frac{\pi}{V_{\pi}} \cdot \frac{V_e}{2}$$

5 Using the identity

$$\cos(\alpha + \beta) = \cos \alpha \cos \beta - \sin \alpha \sin \beta$$

the optical signal represented by Equation (1) can be represented as follows in Equation

(2):

$$E_t(t) = E_o \cos\left[\frac{\phi_{DC}}{2}\right] \cos[\beta_i \sin(\omega_e t + \phi_e(t))] \cdot \cos[\omega_o t + \phi_o(t)] - E_o \sin\left[\frac{\phi_{DC}}{2}\right] \sin[\beta_i \sin(\omega_e t + \phi_e(t))] \cdot \cos[\omega_o t + \phi_o(t)]$$

10 Using the Bessel function expansions

$$\cos(\delta \sin(\omega_m t)) = J_0(\delta) + 2J_2(\delta) \cos(2\omega_m) + 2J_4(\delta) \cos(4\omega_m) + \dots$$

and

$$\sin(\delta \sin(\omega_m t)) = 2J_1(\delta) \sin(\omega_m) + 2J_3(\delta) \sin(3\omega_m) + \dots$$

Equation (2) becomes:

$$15 \quad E_t(t) = E_o \cos\left[\frac{\phi_{DC}}{2}\right] \{J_0(\beta_i) + 2J_2(\beta_i) \cos[2(\omega_e t + \phi_e(t))] + 2J_4(\beta_i) \cos[4(\omega_e t + \phi_e(t))] + \dots\} \cdot \cos[\omega_o t + \phi_o(t)] -$$

$$E_o \sin\left[\frac{\phi_{DC}}{2}\right] \{2J_1(\beta_i) \sin[(\omega_e t + \phi_e(t))] + 2J_3(\beta_i) \sin[3(\omega_e t + \phi_e(t))] + \dots\} \cdot \cos[\omega_o t + \phi_o(t)] \quad (3)$$

Equation (3) becomes:

$$E_t(t) = E_o \cos\left[\frac{\phi_{DC}}{2}\right] \{J_0(\beta_i)\} \cdot \cos[\omega_o t + \phi_o(t)] +$$

$$20 \quad E_o \cos\left[\frac{\phi_{DC}}{2}\right] \{2J_2(\beta_i) \cos[2(\omega_e t + \phi_e(t))] + 2J_4(\beta_i) \cos[4(\omega_e t + \phi_e(t))] + \dots\} \cdot \cos[\omega_o t + \phi_o(t)] -$$

$$E_o \sin\left[\frac{\phi_{DC}}{2}\right] \{2J_1(\beta_i) \sin[(\omega_e t + \phi_e(t))] + 2J_3(\beta_i) \sin[3(\omega_e t + \phi_e(t))] + \dots\} \cdot \cos[\omega_o t + \phi_o(t)]$$

(4)

25 Using the the trig identities

-6-

$$\begin{aligned}
\sin \alpha \sin \beta &= \frac{1}{2} \cos(\alpha - \beta) - \frac{1}{2} \cos(\alpha + \beta) \\
\cos \alpha \cos \beta &= \frac{1}{2} \cos(\alpha - \beta) + \frac{1}{2} \cos(\alpha + \beta) \\
\sin \alpha \cos \beta &= \frac{1}{2} \sin(\alpha + \beta) + \frac{1}{2} \sin(\alpha - \beta) \\
\cos \alpha \sin \beta &= \frac{1}{2} \sin(\alpha + \beta) - \frac{1}{2} \sin(\alpha - \beta)
\end{aligned}$$

the output of the optical modulator can be written as:

$$\begin{aligned}
E_I(t) &= E_o \cos\left[\frac{\phi_{DC}}{2}\right] \{J_0(\beta_i)\} \cdot \cos[\omega_o t + \phi_o(t)] + \\
&+ E_o \cos\left[\frac{\phi_{DC}}{2}\right] J_2(\beta_i) \{\cos(-2\omega_e t - 2\phi_e(t) + \omega_o t + \phi_o(t)) + \cos(2\omega_e t + 2\phi_e(t) + \omega_o t + \phi_o(t))\} + \\
5 \quad &+ E_o \cos\left[\frac{\phi_{DC}}{2}\right] J_4(\beta_i) \{\cos(-4\omega_e t - 4\phi_e(t) + \omega_o t + \phi_o(t)) + \cos(4\omega_e t + 4\phi_e(t) + \omega_o t + \phi_o(t))\} + \dots \\
&+ E_o \sin\left[\frac{\phi_{DC}}{2}\right] J_1(\beta_i) \{\sin(\omega_e t + \phi_e(t) + \omega_o t + \phi_o(t)) + \sin(-\omega_e t - \phi_e(t) + \omega_o t + \phi_o(t))\} + \\
&+ E_o \sin\left[\frac{\phi_{DC}}{2}\right] J_3(\beta_i) \{\sin(3\omega_e t + 3\phi_e(t) + \omega_o t + \phi_o(t)) + \sin(-3\omega_e t - 3\phi_e(t) + \omega_o t + \phi_o(t))\} + \\
&+ E_o \sin\left[\frac{\phi_{DC}}{2}\right] J_5(\beta_i) \{\sin(5\omega_e t + 5\phi_e(t) + \omega_o t + \phi_o(t)) + \sin(-5\omega_e t - 5\phi_e(t) + \omega_o t + \phi_o(t))\} + \dots \quad (5)
\end{aligned}$$

Equation (5) describes the optical carrier and the various generated sidebands. The
10 top line of Equation (5) is the optical carrier signal at a frequency of ω_o . The amplitude of
the carrier frequency is determined by the amplitude of the drive frequency (V_e) which is
included in the factor β_i in the Bessel function J_0 , and by the DC bias on the Mach-
Zehnder interferometer, which sets the fixed phase difference ϕ_{DC} . The second and third
lines show the +/- even sidebands with the optical frequencies ($\omega_o +/- 2\omega_e$), and ($\omega_o +/-$
15 $4\omega_e$), respectively. Ideally there are an infinite number of even sidebands, but from a
practical standpoint, only the first few have sufficient optical power to use in this system.
The fourth, fifth and sixth line in Equation (5) represent the odd sidebands with optical
frequencies of ($\omega_o +/- \omega_e$), ($\omega_o +/- 3\omega_e$), and ($\omega_o +/- 5\omega_e$). Again, the magnitude of each of
these sidebands is controlled by the amplitude of the electrical drive signal and the bias on
20 the Mach-Zehnder Interferometer. Note that the bias of the Mach Zehnder can be
controlled to emphasize the even sidebands ($\phi_{DC} = 0$), or the odd sidebands ($\phi_{DC} = \pi$).

-7-

For this derivation, it is important to note that the phase of the electrical drive signal ϕ_e is present in each of the terms in Equation (5). As such, this phase term becomes part of the millimeter-wave phase and can be used to provide phase modulation of the millimeter-wave signal. If we use an optical filter to eliminate all but the desired

5 sidebands, Equation (5) will be simplified. As an example, if we use an optical filter to eliminate the carrier and all but the +/- 3rd harmonic, the optical signal can be represented by:

$$E_I(t) = E_o \sin\left[\frac{\phi_{DC}}{2}\right] J_3(\beta_i) \{\sin(3\omega_e t + 3\phi_e(t) + \omega_o t + \phi_o(t)) + \sin(-3\omega_e t - 3\phi_e(t) + \omega_o t + \phi_o(t))\}$$

(6)

10 If this optical signal is detected by a sufficiently high frequency photodiode, then the output of the photodiode will envelop the modulated optical signal and be given by:

$$V_{out}(t) = C_1 J_3^2(\beta_i) \{\sin(2 \cdot 3\omega_e t + 2 \cdot 3\phi_e(t))\} \quad (7)$$

where C_1 is a constant related to the responsiveness of the photodiode, the bias on the interferometer and the electrical drive voltage. Note that the frequency of the millimeter-

15 wave signal is $2xN\omega_e$, where N is the sideband number. A typical example is to use a drive frequency of $f_e=15.6$ GHz ($\omega_e = 2\pi f_e$) to achieve a resulting millimeter-wave frequency of 93.6 GHz. However, with this more detailed derivation, it is clear that the phase of the millimeter-wave signal is directly controlled by the phase of the electrical drive signal.

20 In practice, referring to Fig. 1, a digital data transmission device 100 according to the present disclosure will typically comprise a laser source 10, optical waveguide architecture 20, a sideband generator 30, a modulation controller 40, a data mapping unit 50, a phase controller 60, an optical filter 70, an optical amplifier 75, an optical/electrical converter 80, and an electromagnetic transmitting antenna 90, although variations on this

25 general structure are contemplated.

Generally, the optical waveguide architecture comprises a combination of waveguides and optical fibers that are configured to direct optical signals throughout the transmission device. Specifically, the waveguide architecture is configured to direct the

optical carrier and associated sidebands from the laser source 10 to the sideband generator 30, optical filter 70, and optical amplifier 75.

The sideband generator 30 comprises an electrooptic interferometer with first and second waveguide arms, e.g., a Mach-Zehnder interferometer, the structure and function of which is presented in detail in US 2008/0199124. The modulation controller 40 cooperates with the sideband generator 30 and is configured to generate an electrical drive signal that drives the sideband generator 30 at a control voltage that is substantially larger than V_π to generate optical frequency sidebands about the carrier frequency of the optical signal. As is noted in US 2008/0199124, V_π represents the voltage at which a π phase shift is induced between respective arms of the interferometer. The optical filter 70 discriminates between the optical frequency sidebands and the optical carrier frequency such that optical sidebands of interest can be directed through the optical waveguide architecture 20 as an optical millimeter wave signal MMW.

The data mapping unit 50 is configured to generate an encoded data signal representing a digital data input received by the data mapping unit 50. The phase controller 60 is responsive to the data mapping unit 50 and is configured to alter the phase of the electrical drive signal in response to the encoded data signal generated by the data mapping unit 50. In this manner, the phase encoding of the electrical drive signal embodies a direct representation of the digital data input and the sideband generator 30 can be configured such that encoded alterations in the phase of the electrical drive signal are manifested as encoded alterations in the phase of the optical millimeter wave signal MMW. As a result, a phase-encoded representation of the digital data input can be created in the optical millimeter wave signal and the optical/electrical converter 80 can be configured to convert the encoded optical millimeter wave signal MMW to an encoded electrical millimeter wave signal E_{MMW} for transfer to the electromagnetic transmitting antenna 90.

In the embodiment illustrated in Fig. 1, the encoded data signal generated by the data mapping unit 50 can represent a 2-bit code and the phase controller 60 can be configured to alter the phase of the electrical drive signal among four available electrical phase values corresponding to the bit sequence of the 2-bit code:

Table 1.		
Bit Sequence	Phase of the Electrical Drive Signal	Phase of the Millimeter-wave Signal
00	0°	0°
01	15°	90°
10	30°	180°
11	45°	270°

As is illustrated in Table 1, the phase of the resulting millimeter-wave signal MMW can be a direct multiple of the phase of the electrical drive signal. More generally, where the encoded data signal generated by the data mapping unit represents an n-bit code, it is contemplated that the phase controller can be configured to alter the phase of the electrical drive signal among n^2 available electrical phase values corresponding to the bit sequence of the n-bit code.

Referring to Fig. 2, where like reference numerals are used to indicate like structure, it is noted that the present disclosure further contemplates architecture and methodology for phase and amplitude encoding of the millimeter-wave signal MMW. Specifically, the digital data transmission device 100' may further comprise an amplitude controller 65 that is configured to alter the amplitude of the optical millimeter wave signal MMW in further response to the encoded data signal generated by the data mapping unit 50 upon receipt of demultiplexed digital data via demultiplexer 55. In this manner, encoded alterations in the amplitude of the optical millimeter wave signal MMW can be used to create further enhancements to spectral efficiency in the optical millimeter wave signal MMW. The amplitude controller 65 may comprise any suitable device for altering the amplitude of an optical signal and may, for example, be presented as an electrooptic interferometer positioned upstream or downstream of the electrooptic interferometer used for the sideband generator 30.

In the embodiment illustrated in Fig. 2, the encoded data signal generated by the data mapping unit 50 represents a 4-bit code. The phase controller 60 and the amplitude controller 65 are configured to alter the phase of the electrical drive signal and the amplitude of the optical millimeter wave signal among a set of sixteen available phase and

non-zero amplitude values corresponding to the bit sequence of the 4-bit code, an example of which is illustrated in Table 2, where the set of sixteen available phase and amplitude values is defined by eight available phase values and two non-zero amplitude values:

Data	Phase	Amplitude
0000	0	1
0001	$\pi/4$	1
0010	$\pi/2$	1
0011	$3\pi/4$	1
0100	π	1
0101	$5\pi/4$	1
0110	$3\pi/2$	1
0111	$7\pi/4$	1
1000	0	3
1001	$\pi/4$	3
1010	$\pi/2$	3
1011	$3\pi/4$	3
1100	π	3
1101	$5\pi/4$	3
1110	$3\pi/2$	3
1111	$7\pi/4$	3

5

More generally, where the encoded data signal generated by the data mapping unit represents an n-bit code, the phase controller and the amplitude controller can be configured to alter the phase of the electrical drive signal and the amplitude of the optical millimeter wave signal among n^2 available phase and amplitude values corresponding to the bit sequence of the n-bit code. Preferably, the set of n^2 available phase and amplitude values is defined by at least $n^2/4$ and as many as $n^2/2$ available phase values and at least $n^2/8$ and as many as $n^2/4$ non-zero amplitude values. For example, in the case of the 4-bit code illustrated above, it is contemplated that the set of sixteen available phase and amplitude values would preferably be defined by at least four and as many as eight available phase values and at least two and as many as four non-zero amplitude values.

15

Fig. 2 also presents a schematic representation of the case where the digital data transmission device 100 further comprises a millimeter wave receiver 95 that is positioned to receive the encoded electrical millimeter wave signal E_{MMW} transmitted by the

-11-

electromagnetic transmitting antenna 90. For example, the millimeter wave receiver 95 typically comprises an electromagnetic receiving antenna, a phase shift detector, and a data recovery unit configured to receive and decode the encoded electrical millimeter wave signal. The phase shift detector can be presented in any conventional or yet-to-be developed configuration. For example, it is contemplated that the phase shift detector may 5 comprise a phase-locked loop where a local oscillator is phase-locked to the carrier frequency of the incoming signal and the phase of the local oscillator and the phase of the incoming signal are compared to detect the phase shift.

It is noted that recitations herein of a component of the present disclosure being 10 “configured” in a particular way, “configured” to embody a particular property, or function in a particular manner, are structural recitations, as opposed to recitations of intended use. More specifically, the references herein to the manner in which a component is “configured” denotes an existing physical condition of the component and, as such, is to be taken as a definite recitation of the structural characteristics of the 15 component.

It is noted that terms like “preferably,” “commonly,” and “typically,” when utilized herein, are not utilized to limit the scope of the claimed invention or to imply that certain features are critical, essential, or even important to the structure or function of the claimed invention. Rather, these terms are merely intended to identify particular aspects of an 20 embodiment of the present disclosure or to emphasize alternative or additional features that may or may not be utilized in a particular embodiment of the present disclosure.

For the purposes of describing and defining the present invention it is noted that the terms “substantially” and “approximately” are utilized herein to represent the inherent degree of uncertainty that may be attributed to any quantitative comparison, value, 25 measurement, or other representation. The terms “substantially” and “approximately” are also utilized herein to represent the degree by which a quantitative representation may vary from a stated reference without resulting in a change in the basic function of the subject matter at issue.

Having described the subject matter of the present disclosure in detail and by 30 reference to specific embodiments thereof, it will be apparent that modifications and variations are possible without departing from the scope of the invention defined in the

-12-

appended claims. More specifically, although some aspects of the present disclosure are identified herein as preferred or particularly advantageous, it is contemplated that the present disclosure is not necessarily limited to these aspects.

5 It is noted that one or more of the following claims utilize the term “wherein” as a transitional phrase. For the purposes of defining the present invention, it is noted that this term is introduced in the claims as an open-ended transitional phrase.

-13-

CLAIMS

1. A digital data transmission device comprising optical waveguide architecture, a
5 sideband generator, a modulation controller, an optical filter, a data mapping unit, and a
phase controller, wherein:

the optical waveguide architecture is configured to direct an optical signal through
the sideband generator and the optical filter;

10 the sideband generator comprises an electrooptic interferometer comprising first
and second waveguide arms;

the modulation controller is configured to generate an electrical drive signal to
drive the sideband generator at a control voltage that is substantially larger than V_π to
generate optical frequency sidebands about a carrier frequency of the optical signal, where
 V_π represents the voltage at which a π phase shift is induced between respective arms of
15 the interferometer;

the optical filter is configured to discriminate between the optical frequency
sidebands and the optical carrier frequency such that optical sidebands of interest can be
directed through the optical waveguide architecture as an optical millimeter wave signal;

20 the data mapping unit is configured to generate an encoded data signal representing
a digital data input received by the data mapping unit;

the phase controller is configured to alter the phase of the electrical drive signal in
response to the encoded data signal generated by the data mapping unit;

25 the sideband generator is configured such that encoded alterations in the phase of
the electrical drive signal are manifested as encoded alterations in the phase of the optical
millimeter wave signal, creating an encoded representation of the digital data input in the
optical millimeter wave signal.

30

-14-

2. A device as claimed in claim 1 wherein
the encoded data signal generated by the data mapping unit represents a 2-bit code;
and
the phase controller is configured to alter the phase of the electrical drive signal
5 among four available electrical phase values corresponding to the bit sequence of the 2-bit
code.
3. A device as claimed in claim 1 wherein
the encoded data signal generated by the data mapping unit represents an n-bit
10 code; and
the phase controller is configured to alter the phase of the electrical drive signal
among n^2 available electrical phase values corresponding to the bit sequence of the n-bit
code.
- 15 4. A device as claimed in claim 3 wherein the phase of the optical millimeter wave signal
is a multiple of the phase of the electrical drive signal.
5. A device as claimed in claim 1 wherein the digital data transmission device further
comprises an amplitude controller configured to alter the amplitude of the optical
20 millimeter wave signal in further response to the encoded data signal generated by the data
mapping unit, such that encoded alterations in the amplitude of the optical millimeter
wave signal create a further encoded representation of the digital data input in the optical
millimeter wave signal.
- 25 6. A device as claimed in claim 5 wherein the amplitude controller comprises an
electrooptic interferometer.
7. A device as claimed in claim 5 wherein the amplitude controller is positioned upstream
or downstream of the electrooptic interferometer of the sideband generator.

30

-15-

8. A device as claimed in claim 5 wherein

the encoded data signal generated by the data mapping unit represents a 4-bit code;

and

the phase controller and the amplitude controller are configured to alter the phase

5 of the electrical drive signal and the amplitude of the optical millimeter wave signal
among a set of sixteen available phase and non-zero amplitude values corresponding to the
bit sequence of the 4-bit code.

9. A device as claimed in claim 8 wherein the set of sixteen available phase and amplitude

10 values is defined by eight available phase values and two non-zero amplitude values.

10. A device as claimed in claim 8 wherein the set of sixteen available phase and

amplitude values is defined by at least four and as many as eight available phase values

and at least two and as many as four non-zero amplitude values.

15

11. A device as claimed in claim 5 wherein

the encoded data signal generated by the data mapping unit represents an n-bit
code; and

the phase controller and the amplitude controller are configured to alter the phase

20 of the electrical drive signal and the amplitude of the optical millimeter wave signal
among n^2 available phase and amplitude values corresponding to the bit sequence of the n-
bit code.

12. A device as claimed in claim 11 wherein the set of n^2 available phase and amplitude

25 values is defined by at least $n^2/4$ and as many as $n^2/2$ available phase values and at least
 $n^2/8$ and as many as $n^2/4$ non-zero amplitude values.

13. A device as claimed in claim 11 wherein the set of n^2 available phase and amplitude

values is defined by more available phase values than non-zero amplitude values.

30

-16-

14. A device as claimed in claim 1 wherein:

the digital data transmission device further comprises an optical/electrical converter and an electromagnetic transmitting antenna; and

the optical/electrical converter is configured to convert the encoded optical millimeter wave signal to an encoded electrical millimeter wave signal and transfer the encoded electrical millimeter wave signal to the electromagnetic transmitting antenna.

15. A device as claimed in claim 14 wherein:

the digital data transmission device further comprises a millimeter wave receiver positioned to receive the encoded electrical millimeter wave signal transmitted by the electromagnetic transmitting antenna;

the millimeter wave receiver comprises an electromagnetic receiving antenna, a phase shift detector, and a data recovery unit configured to receive and decode the encoded electrical millimeter wave signal.

15

16. A device as claimed in claim 1 wherein the digital data transmission device further comprises a carrier signal laser source optically coupled to the waveguide architecture.

20 17. A method of transmitting digital data, wherein the method comprises:

directing an optical signal through a sideband generator comprising an electrooptic interferometer comprising first and second waveguide arms;

driving the sideband generator with an electrical drive signal at a control voltage that is substantially larger than V_{π} to generate optical frequency sidebands about a carrier frequency of the optical signal, where V_{π} represents the voltage at which a π phase shift is induced between respective arms of the electrooptic interferometer;

discriminating between the optical frequency sidebands and the optical carrier frequency to generate an optical millimeter wave signal;

generating an encoded data signal representing a digital data input;

-17-

altering the phase of the electrical drive signal in response to the encoded data signal such that encoded alterations in the phase of the electrical drive signal are manifested as encoded alterations in the phase of the optical millimeter wave signal, creating an encoded representation of the digital data input in the optical millimeter wave
5 signal.

18. A method as claimed in claim 17 wherein the method further comprises:

altering the amplitude of the optical millimeter wave signal in further response to the encoded data signal such that encoded alterations in the amplitude of the optical
10 millimeter wave signal create a further encoded representation of the digital data input in the optical millimeter wave signal.




FIG. 1




FIG. 2

INTERNATIONAL SEARCH REPORT

International application No

PCT/US2009/042532

A. CLASSIFICATION OF SUBJECT MATTER
 INV. H04B10/155 G01V8/00

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

H04B G01V

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the international search (name of data base and, where practical, search terms used)

EPO-Internal, INSPEC

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
Y	KAWANISHI T ET AL: "Millimeter-wave generation and baseband modulation by using reciprocating optical modulation for radio-on-fiber systems in v-band" MICROWAVE PHOTONICS, 2003. MWP 2003 PROCEEDINGS. INTERNATIONAL TOPICAL MEETING ON BUDAPEST, HUNGARY 10-12 SEPT. 2003, PISCATAWAY, NJ, USA, IEEE, 10 September 2003 (2003-09-10), pages 325-328, XP010790966 ISBN: 978-0-7803-8691-4 page 326, right-hand column; figure 1 -----	1-18
Y	EP 0 825 733 A (NIPPON ELECTRIC CO [JP]) 25 February 1998 (1998-02-25) column 11, line 25 - column 11, line 55; figure 18 ----- -/--	1-18

Further documents are listed in the continuation of Box C.

See patent family annex.

* Special categories of cited documents:

"A" document defining the general state of the art which is not considered to be of particular relevance

"E" earlier document but published on or after the international filing date

"L" document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)

"O" document referring to an oral disclosure, use, exhibition or other means

"P" document published prior to the international filing date but later than the priority date claimed

"T" later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention

"X" document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone

"Y" document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art.

"&" document member of the same patent family

Date of the actual completion of the international search

16 July 2009

Date of mailing of the international search report

23/07/2009

Name and mailing address of the ISA/

European Patent Office, P.B. 5818 Patentlaan 2
 NL - 2280 HV Rijswijk
 Tel. (+31-70) 340-2040,
 Fax: (+31-70) 340-3016

Authorized officer

Phillips, Simon

INTERNATIONAL SEARCH REPORT

International application No

PCT/US2009/042532

C(Continuation). DOCUMENTS CONSIDERED TO BE RELEVANT

Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
A	<p>YE ZHANG ET AL: "Photonic generation of millimeter-wave-band 16-QAM and 16-ASK signals based on orthogonal polarization multiplexing" MICROWAVE AND MILLIMETER WAVE TECHNOLOGY, 2008. ICMMT 2008. INTERNATIONAL CONFERENCE ON, IEEE, PISCATAWAY, NJ, USA, 21 April 2008 (2008-04-21), pages 1797-1798, XP031270881 ISBN: 978-1-4244-1879-4 abstract; figure 1</p>	1-18
A	<p>US 2002/171900 A1 (ONO TAKASHI [JP] ET AL) 21 November 2002 (2002-11-21) abstract; figure 6</p>	1-18
A	<p>TETSUYA KAWANISHI ET AL: "High-Speed Control of Lightwave Amplitude, Phase, and Frequency by Use of Electrooptic Effect" IEEE JOURNAL OF SELECTED TOPICS IN QUANTUM ELECTRONICS, IEEE SERVICE CENTER, PISCATAWAY, NJ, US, vol. 13, no. 1, 1 January 2007 (2007-01-01), pages 79-91, XP011163496 ISSN: 1077-260X abstract; figures 19,24</p>	1-18

INTERNATIONAL SEARCH REPORT

Information on patent family members

International application No

PCT/US2009/042532

Patent document cited in search report		Publication date	Patent family member(s)	Publication date
EP 0825733	A	25-02-1998	JP 3027944 B2	04-04-2000
			JP 10112688 A	28-04-1998
			US 6097525 A	01-08-2000
<hr/>				
US 2002171900	A1	21-11-2002	JP 2002258228 A	11-09-2002
<hr/>				