




(86) Date de dépôt PCT/PCT Filing Date: 2004/09/01
 (87) Date publication PCT/PCT Publication Date: 2005/03/10
 (45) Date de délivrance/Issue Date: 2017/08/08
 (85) Entrée phase nationale/National Entry: 2006/03/01
 (86) N° demande PCT/PCT Application No.: GB 2004/003745
 (87) N° publication PCT/PCT Publication No.: 2005/022186
 (30) Priorité/Priority: 2003/09/01 (GB0320352.8)

(51) Cl.Int./Int.Cl. *H04B 14/08* (2006.01),
G01S 19/01 (2010.01), *G01S 19/30* (2010.01),
H04L 27/18 (2006.01)
 (72) Inventeurs/Inventors:
PRATT, ANTHONY RICHARD, GB;
OWEN, JOHN IVOR REWBRIDGE, GB
 (73) Propriétaire/Owner:
SECRETARY OF STATE FOR DEFENCE, GB
 (74) Agent: RIDOUT & MAYBEE LLP

(54) Titre : SIGNAUX DE MODULATION DESTINES A UN SYSTEME DE NAVIGATION PAR SATELLITE
 (54) Title: MODULATION SIGNALS FOR A SATELLITE NAVIGATION SYSTEM



(57) Abrégé/Abstract:

Embodiments of the present invention relate to a modulation system in which an m-level, $m > 2$, digital subcarrier is used to modulate a signal.

(12) INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(19) World Intellectual Property
Organization
International Bureau




(43) International Publication Date
10 March 2005 (10.03.2005)

PCT

(10) International Publication Number
WO 2005/022186 A1

- (51) International Patent Classification⁷: **G01S 1/00**, H04B 1/707
- (21) International Application Number: PCT/GB2004/003745
- (22) International Filing Date: 1 September 2004 (01.09.2004)
- (25) Filing Language: English
- (26) Publication Language: English
- (30) Priority Data: 0320352.8 1 September 2003 (01.09.2003) GB
- (71) Applicant (for all designated States except US): **SECRETARY OF STATE FOR DEFENCE [GB/GB]**; DSTL, Porton Down, Salisbury, Wiltshire SP4 0JQ (GB).
- (72) Inventors; and
- (75) Inventors/Applicants (for US only): **PRATT, Anthony, Richard [GB/GB]**; 1 Brixworth Hall Park, Brixworth, Northants NN6 9DE (GB). **OWEN, John, Ivor, Rewbridge [GB/GB]**; Dstl Farnborough, Ively Road, Farnborough GU14 0LX (GB).
- (74) Agent: **HUTCHINSON, Glenn**; Harrison Goddard Foote, Fountain Precinct, Balm Green, Sheffield S1 2JA (GB).
- (81) Designated States (unless otherwise indicated, for every kind of national protection available): AE, AG, AL, AM, AT, AU, AZ, BA, BB, BG, BR, BW, BY, BZ, CA, CH, CN, CO, CR, CU, CZ, DE, DK, DM, DZ, EC, EE, EG, ES, FI, GB, GD, GE, GH, GM, HR, HU, ID, IL, IN, IS, JP, KE, KG, KP, KR, KZ, LC, LK, LR, LS, LT, LU, LV, MA, MD, MG, MK, MN, MW, MX, MZ, NA, NI, NO, NZ, OM, PG, PH, PL, PT, RO, RU, SC, SD, SE, SG, SK, SL, SY, TJ, TM, TN, TR, TT, TZ, UA, UG, US, UZ, VC, VN, YU, ZA, ZM, ZW.
- (84) Designated States (unless otherwise indicated, for every kind of regional protection available): ARIPO (BW, GH, GM, KE, LS, MW, MZ, NA, SD, SL, SZ, TZ, UG, ZM, ZW), Eurasian (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM), European (AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HU, IE, IT, LU, MC, NL, PL, PT, RO, SE, SI, SK, TR), OAPI (BF, BJ, CF, CG, CI, CM, GA, GN, GQ, GW, ML, MR, NE, SN, TD, TG).
- Published:**
- with international search report
 - before the expiration of the time limit for amending the claims and to be republished in the event of receipt of amendments
- For two-letter codes and other abbreviations, refer to the "Guidance Notes on Codes and Abbreviations" appearing at the beginning of each regular issue of the PCT Gazette.

(54) Title: MODULATION SIGNALS FOR A SATELLITE NAVIGATION SYSTEM



(57) Abstract: Embodiments of the present invention relate to a modulation system in which an m-level, $m > 2$, digital subcarrier is used to modulate a signal.

WO 2005/022186 A1

MODULATION SIGNALS FOR A SATELLITE NAVIGATION SYSTEM

Field of the Invention

The invention relates to modulation signals, systems and methods such as, for example, navigation and positioning signals, systems and methods.

5 Background to the invention

Satellite Positioning Systems (SPS) rely on the passive measurement of ranging signals broadcast by a number of satellites, or ground-based or airborne equivalents, in a specific constellation or group of constellations. An on-board clock is used to generate a regular and usually continual series of events, often known as 'epochs', whose time of occurrence is coded into a random or pseudo-random code
10 (known as a spreading code). As a consequence of the pseudo-random or random features of the time epoch encoding sequence, the spectrum of the output signal is spread over a frequency range determined by a number of factors including the rate of change of the spreading code elements and the waveform used for the spreading signal. Typically, the spreading waveform is rectangular and has a sinc function power spectrum.

15 The ranging signals are modulated onto a carrier signal for transmission to passive receivers. Applications are known that cover land, airborne, marine and space use. Typically, binary phase shift keying is employed to modulate the carrier signal, which, itself, has a constant magnitude. Usually, at least two such signals are modulated onto the same carrier in phase quadrature. The resulting carrier signal retains its constant envelope but has four phase states depending upon the two independent
20 input signals. However, it will be appreciated that two modulating signals do not need to have the same carrier magnitude. It is possible for a constant carrier magnitude of the combined signal to be maintained by appropriate selection of corresponding phases other than $\pi/2$ radians.

An example of such a satellite positioning system is the Global Positioning System (GPS). Generally, the GPS operates using a number of frequencies such as, for example, L1, L2 and L5, which are
25 centred at 1575.42 MHz, 1227.6 MHz and 1176.45 MHz respectively. Each of these signals is modulated by respective spreading signals. As will be appreciated by those skilled in the art, a Coarse Acquisition (CA) code signal emitted by the GPS Satellite Navigation System is broadcast on the L1 frequency of 1575.42MHz with a spreading code rate (chip rate) of 1.023MHz. The CA has a rectangular spreading waveform and is categorised as BPSK-R1. The GPS signal structure is such
30 that the signal broadcast by the satellites on the L1 frequency has a second component in phase quadrature, which is known as the precision code (P(Y) code) and made available to authorised users only. The P(Y) signal is BPSK modulated with a spreading code at 10.23MHz with a magnitude which is 3dB lower in signal power than the CA code transmission. Consequently, the Q component

has a magnitude which is 0.7071 (-3dB) of the magnitude of the I component. It will be appreciated by those skilled in the art that the phase angles of these states of these signals are $\pm 35.265^\circ$ in relation to the $\pm I$ axis (phase of the CA code signal as specified in ICD GPS 200C). One skilled in the art also appreciates that the P code is a function of or is encrypted by the Y code. The Y code is used to encrypt the P code. One skilled in the art appreciates that the L1 signal, containing both I & Q components, and the L2 signal can be represented, for a given satellite, i , as

$$S_{L1i}(t) = A_P p_i(t) d_i(t) \cos(\omega_1 t) + A_C c_i(t) d_i(t) \sin(\omega_1 t), \text{ and}$$

$$S_{L2i}(t) = B_P p_i(t) d_i(t) \cos(\omega_2 t)$$

where

10 A_P and A_C are the amplitudes of the P and CA codes, typically $A_P = 2A_C$;

B_P is the amplitude of the L2 signal;

ω_1 and ω_2 are the L1 and L2 carrier frequencies;

$p_i(t)$ represents the P(Y) ranging code and is a pseudo-random sequence with a chip rate of 10.23 Mcbps. The P code has a period of exactly 1 week, taking values of +1 and -1;

15 $c_i(t)$ represents the CA ranging code and is a 1023 chip Gold code, taking values of +1 and -1;

$d_i(t)$ represents the data message, taking values of +1 and -1.

A satellite constellation typically comprises 24 or more satellites often in similar or similarly shaped orbits but in a number of orbital planes. The transmissions from each satellite are on the same nominal carrier frequency in the case of code division access satellites (such as GPS) or on nearby related frequencies such as GLONASS. The satellites transmit different signals to enable each one to be separately selected even though several satellites are simultaneously visible.

The signals from each satellite, in a CDMA system like GPS, are distinguished from each one another by means of the different spreading codes and/or differences in the spreading code rates, that is, the $p_i(t)$ and $c_i(t)$ sequences. Nevertheless, as will be appreciated from the power spectrum 100 shown in figure 1 there remains significant scope for interference between the signals transmitted by the satellites. Figure 1 shows power spectra 100 for the CA and P(Y) codes. The power spectrum 102 for the CA code has maximum power at the carrier frequency L1 and zeros at multiples of the fundamental frequency, 1.023MHz, of the CA code. For example, it can be appreciated that zeros occur either side of the carrier frequency at $\pm 1.023\text{MHz}$, $\pm 2.046\text{MHz}$ etc. Similarly, the power

spectrum 104 for the P(Y) code has a maximum amplitude centred on the L1 and L2 frequencies, with zeros occurring at multiples of $\pm 10.23\text{MHz}$ as is expected with a sinc function waveform.

It is known to further modulate the ranging codes using a sub-carrier, that is, a further signal is convolved with the P codes and/or CA codes to create Binary Offset Carrier (BOC) modulation as is known within the art see, for example, J. W. Betz, "*Binary Offset Carrier Modulation for Radionavigation*", Navigation, Vol. 48, pp227-246, Winter 2001-2002. Standard BOC modulation is illustrated in figure 2. Figure 2 illustrates the combination of a portion of a CA code with a subcarrier signal to produce the BOC signal used to modulate a carrier such as, for example, L1. It can be appreciated that the BOC signal is a rectangular square wave and can be represented as, for example, $c_i(t) \cdot \text{sign}(\sin(2\pi f_s t))$, where f_s is the frequency of the subcarrier. One skilled in the art understands that $\text{BOC}(f_s, f_c)$ denotes Binary Offset Carrier modulation with a subcarrier frequency of f_s and a code rate (or chipping rate) of f_c . Using binary offset carriers results in the following signal descriptions of the signals emitted from the satellite:

$$S_{L1i}(t) = A_m sc_{im}(t) m_i(t) d_i(t) \cos(\omega_1 t) + A_c sc_{ig}(t) g_i(t) d_i(t) \sin(\omega_1 t) = I_{SL1i}(t) + Q_{SL1i}(t), \text{ and}$$

$$S_{L2i}(t) = B_m sc_{im}(t) m_i(t) d_i(t) \cos(\omega_2 t)$$

where

A_m , A_c and B_m are amplitudes;

$m_i(t)$ is an m-code BOC(10,5) signal;

$g_i(t)$ is a Galileo open service range code;

$sc_{im}(t)$ represents the sub-carrier signal for $m_i(t)$;

$sc_{ig}(t)$ represents a subcarrier signal for $c_i(t)$;

ω_1 and ω_2 are the L1 and L2 carrier frequencies;

Figure 2 also illustrates power spectra for a BPSK-R1 code and pair of BOC signals, that is, BOC(2,1) and BOC(10,5). The first spectrum 202 corresponds to BPSK-R1 code. The second power spectrum 204 corresponds to the BOC(2,1) code and the third power spectrum 206 corresponds to the BOC(10,5) code. It can be appreciated that the side lobes 208 of the BOC(2,1) signal have a relatively large magnitude. Similarly, the illustrated side lobe 210 of the BOC(10,5) signal has a relatively large magnitude. One skilled in the art appreciates that the energy in the side lobes are a source of interference.

It is an object of embodiments of the present invention to at least mitigate the problems of the prior art.

Summary of Invention

Accordingly, a first aspect of embodiments of the present invention provides an m-level
5 modulation signal comprising m signal amplitudes, where $m > 2$, for modulating a first signal.

A second aspect of embodiments of the present invention provides a method of generating a transmission signal comprising a carrier signal, the method comprising the step of combining a plurality of subcarrier modulation signals with the carrier signal.

A third aspect of embodiments of the present invention provides a ranging system
10 comprising: means for generating a ranging code; means for generating a signal or implementing a method according to the invention, for generating a transmission signal; and means for transmitting the signal.

A fourth aspect of embodiments of the present invention provides a system comprising:
memory for storing at least one of a plurality of selectable phase states and selectable
15 amplitude states; the memory being responsive to at least one of a ranging code signal, a system clock signal and a subcarrier signal to produce a carrier signal bearing at least one of phase and amplitude modulation to produce a transmission signal.

A fifth aspect of embodiments of the present invention provides a method of generating a subcarrier modulation signal for modulating a further signal, the method comprising the step
20 of multiplexing or selectively combining portions of first and second subcarriers to produce the subcarrier modulation signal.

A sixth aspect of embodiments of the present invention provides a ranging system comprising: means for generating a ranging code; means for generating carrier signal; means for generating a plurality of subcarrier signals; and means for combining the ranging
25 code, carrier signal and the subcarrier signals to produce an output signal.

A seventh aspect of embodiments of the present invention provides a system comprising memory for storing at least one of a plurality of selectable phase states and selectable amplitude states; the memory being responsive to at least one of a ranging code signal, a system clock signal and a subcarrier signal to produce a carrier signal bearing at least one of
5 phase and amplitude modulation to produce a transmission signal.

Advantageously, embodiments of the present invention provide significantly more control over the shape of the power spectra of signals, that is, the distribution of energy within those signals.

Other aspects of the present invention are described and defined in the claims.

10 Brief Description of the Invention

Embodiments of the present invention will now be described, by way of example, only with reference to the accompanying drawings in which:

figure 1 shows a power spectrum of a pair of ranging code;

figure 2 illustrates power spectra of a ranging code (BPSK-R1) and BOC(10,5) signals;

15 figure 3 illustrates a multi-level sub-carrier;

figure 4 illustrates the phase states for at least a pair of multilevel subcarriers according to embodiments of the present invention;

figure 5 depicts a power spectrum of a prior art subcarrier and a subcarrier according to embodiments of the present invention;

figure 6 illustrates phase states for a subcarrier according to embodiments of the present invention;

figure 7 illustrates in phase and quadrature phase subcarriers according to embodiments of the present invention;

figure 8 illustrates phase states of a subcarrier according to an embodiment of the present invention;

figure 9 shows subcarriers according to embodiments of the present invention;

figure 10 depicts power spectra of subcarriers according to embodiments of the present invention;

figure 11 illustrates subcarriers according to embodiments of the present invention;

figure 12 shows an alternative subcarrier waveform according to an embodiment of the present invention;

figure 13 illustrates, schematically, a transmitter using subcarriers according to embodiments of the present invention; and

figure 14 illustrates a further embodiment of a transmitter according to an embodiment.

15

Detailed Description of the Drawings

Referring to figure 3, there is shown a first embodiment of a subcarrier 300. It can be appreciated that the sub-carrier is a 5-level approximation of a sinusoidal signal 302. It can be appreciated that the signal levels are (+1, +1/√2, 0, -1/√2, -1). Furthermore, it will be appreciated that the levels are the projections onto the x or I axis of a rotating vector at angles of π/4 radians having a unit magnitude. It will be further appreciated that, given the in-phase and quadrature-phase components of, for example, S_{LI} , that is, $A_m sc_m(t) m_i(t) d_i(t) \cos(\omega_i t) = I_{S_{LI}}(t)$ and $A_c sc_c(t) g_i(t) d_i(t) \sin(\omega_i t) = Q_{S_{LI}}(t)$, the magnitude of the signal will be such that it is constant since the projection of the quadrature phase component onto the y or Q axis will also take the values (+1, +1/√2, 0, -1/√2, -1).

25

It will be appreciated that there are preferably restrictions on the combinations of signals, at least one of which is that a constant modulus signal should be maintained. The constraints are (1) that "+1" or "-1" on the in-phase component can only occur in conjunction with "0" on the quadrature phase

component and visa versa and (2) " $\pm 1/\sqrt{2}$ " can only occur on both phases simultaneously. The magnitudes of the in-phase and quadrature phase components of the spreading signals, $sc_{ig}(t)$ or $sc_{im}(t)$, can be plotted on an Argand diagram 400 such as is shown in figure 4. The waveforms for the I and Q components are thus built from the following signal element sequences:

- 5 I phase - $(+1/\sqrt{2}, +1, +1/\sqrt{2}, 0)$ representing a +1 signal
- I phase - $(-1/\sqrt{2}, -1, -1/\sqrt{2}, 0)$ representing a -1 signal
- Q phase - $(+1/\sqrt{2}, 0, -1/\sqrt{2}, -1)$ representing a +1 signal
- Q phase - $(-1/\sqrt{2}, 0, +1/\sqrt{2}, +1)$ representing a -1 signal.

10 Any combination of I or Q signal sequences can be chosen from the above set within the constraint of a constant magnitude carrier signal, computed as $(I^2+Q^2)^{1/2}$. It will be clear to those skilled in the art, that there are many other equivalent sets of sequences which may be chosen from the set of 5-levels satisfying the criterion of a constant carrier envelope. It can be appreciated that the magnitudes of the subcarriers on the I and Q channels can be thought of as being analogous to the states of an 8-PSK signal. Therefore, such a pair of 5-level subcarrier carrier signals can be thought of as 8 phase

15 subcarrier signals.

Figure 5 illustrates the effect of using a stepped or m-level, $m>2$, subcarrier waveform. Referring to figure 5 there is shown a pair 500 of power spectra. The first power spectrum 502, illustrated using the dotted line, represents the spectrum of a BOC(2,2) subcarrier. It can be appreciated that the energy of the subcarrier is contained within progressively reducing side lobes 504, 506, 508 and 510.

20 The second power spectrum 512 represents the power spectrum of a BOC(2,2) signal that used 8 phase subcarrier signals, that is, 8 phase amplitudes, represented by BOC8(2,2). More generally, $BOC_m(f_s, f_c)$ represents an m-phase subcarrier signal of having a frequency of f_s and a chipping rate of f_c . It can be appreciated that the spectrum 512 of the BOC8(2,2) signal has a number of side lobes 514, 516, 518, 520, 522 and 524. Of those side lobes, it can be seen that the 1st to 4th side lobes are

25 significantly reduced, that is, they comprise significant less energy, as compared to the side lobes of the BOC(2,2) signal spanning the same frequencies. The significant reduction in the 1st to 4th side lobes can be beneficial in situations in which one skilled in the art wishes to use the frequency spectrum spanned by the side lobes for other transmissions.

It will be appreciated by those skilled in the art the BOC8(2,2) has significantly improved interference

30 properties as determined using Spectral Separation Coefficients (SSC) and self-SSCs as is well understood by those skilled in the art, that is, the spectral coupling between a reference signal and BOC(2,2) is greater than the spectral coupling between a reference signal and BOC8(2,2). For

example, a BOC8(2,2) signal exhibits a 10-12 dB improvement in spectral isolation as compared to a conventional BOC(2,2) signal. Further information on the relationship between SSC and signals according to embodiments of the present invention can be found in, for example, Pratt & Owen; BOC Modulation Waveforms, IoN Proceedings, GPS 2003
 5 Conference, Portland, September 2003.

Furthermore, embodiments of the present invention utilise the magnitude and duration of the subcarrier to influence, that is, control the energy in harmonics of the resulting modulating waveform. For example, referring still to figure 5, it can be appreciated that additional spectral nulls appear in the BOC8(2,2) spectrum at substantially 6MHz and 10MHz offset
 10 from the carrier whereas there are no such nulls in the conventional BOC(2,2) signal. The location of the nulls is influenced by at least one of the magnitude and duration of the steps in the multilevel subcarrier. More specifically, the nulls can be steered to desired locations by changing either of these two elements, that is, the position of the nulls is influenced by these two elements. Appendix A contains an indication of the relationship between the
 15 spectra of signals according to embodiments of the present invention and the magnitude and duration of the steps.

Referring to figure 6, there is shown subcarrier states or amplitudes for I and Q signals for a further BOC8 signal, that is, a binary offset carrier having eight states. It can be appreciated that the eight states can be represented by, or correspond to, subcarrier amplitudes chosen
 20 from the set $(-\sqrt{3}/2, -1/2, +1/2, +\sqrt{3}/2)$ ie four states or signal amplitudes rather than the five states or signal amplitudes described above. Therefore, the I and Q components are constructed from the following signal elements such that $\sqrt{(\cos^2 \theta + \sin^2 \theta)} = 1$, that is, $\pm\sqrt{3}/2$ can only occur in conjunction with $\pm 1/2$, are as follows:

25 I phase - $(+1/2, +\sqrt{3}/2, +\sqrt{3}/2, +1/2)$ representing a +1 chip of a ranging code signal

I phase - $(-1/2, -\sqrt{3}/2, -\sqrt{3}/2, -1/2)$ representing a -1 chip of a ranging code signal

Q phase - $(+\sqrt{3}/2, +1/2, -1/2, -\sqrt{3}/2)$ representing a +1 chip of a ranging code signal

Q phase - $(-\sqrt{3}/2, -1/2, +1/2, +\sqrt{3}/2,)$ representing a -1 chip of a ranging code signal.

It will be appreciated that the states 1 to 8 shown in figure 6 are not equidistantly disposed circumferentially. The transitions between states 2&3, 4&5, 6&7, 8&1 are larger in angular step than the transitions between states 1&2, 3&4, 5&6, 7&8. It will be appreciated that
5 when these states are translated into subcarrier amplitudes, the duration of a given amplitude will depend on the duration or dwell time of a corresponding state, that is, the durations for which the subcarrier remains in any

given state may no longer be equal unlike the states of figure 4 above. The dwell times are a matter of design choice such as, for example, to minimise the mean square difference between a stepped waveform and a sinusoid. Figure 7a illustrates the subcarriers 700 and 702 corresponding to the states shown in figure 6. It can be appreciated that the durations of within each state the subcarriers 700 and 702 are equal. The Q channel subcarrier magnitudes will follow substantially the same pattern as described above but phase shifted by $\pi/2$ radians. The subcarrier 702 for the Q channel is shown in dotted form in figure 7. It will be appreciated that such subcarriers provide a constant envelope magnitude since $(I^2+Q^2)^{1/2}=1$ for all amplitude combinations. However, referring to figure 7b, there is shown a pair of subcarriers 704 and 706 in which the durations at each state are unequal. It will be appreciated that not all amplitude combinations satisfy $(I^2+Q^2)^{1/2}=1$. Therefore, the transmitted signal will not have a constant envelope.

It will be appreciated by those skilled in the art that a stepped half cycle of the subcarrier corresponds to one chip. However, other embodiments can be realised in which other multiples of half cycles correspond to a chip. For example, embodiments can be realised in which two half cycles of a subcarrier correspond to a chip. In such embodiments the signals for the I and Q channels would be

I phase - $(+1/2, +\sqrt{3}/2, +\sqrt{3}/2, +1/2, -1/2, -\sqrt{3}/2, -\sqrt{3}/2, -1/2)$ representing a +1 signal

I phase - $(-1/2, -\sqrt{3}/2, -\sqrt{3}/2, -1/2, +1/2, +\sqrt{3}/2, +\sqrt{3}/2, +1/2)$ representing a -1 signal

Q phase - $(+\sqrt{3}/2, +1/2, -1/2, -\sqrt{3}/2, -\sqrt{3}/2, -1/2, +1/2, +\sqrt{3}/2)$ representing a +1 signal

Q phase - $(-\sqrt{3}/2, -1/2, +1/2, +\sqrt{3}/2, +\sqrt{3}/2, +1/2, -1/2, -\sqrt{3}/2)$ representing a -1 signal.

Similarly, embodiments realised using three half cycles per chip would produce

I phase - $(+1/2, +\sqrt{3}/2, +\sqrt{3}/2, +1/2, -1/2, -\sqrt{3}/2, -\sqrt{3}/2, -1/2, +1/2, +\sqrt{3}/2, +\sqrt{3}/2, +1/2)$ representing a +1 signal

I phase - $(-1/2, -\sqrt{3}/2, -\sqrt{3}/2, -1/2, +1/2, +\sqrt{3}/2, +\sqrt{3}/2, +1/2, -1/2, -\sqrt{3}/2, -\sqrt{3}/2, -1/2)$ representing a -1 signal

Q phase - $(+\sqrt{3}/2, +1/2, -1/2, -\sqrt{3}/2, -\sqrt{3}/2, -1/2, +1/2, +\sqrt{3}/2, +\sqrt{3}/2, +1/2, -1/2, -\sqrt{3}/2)$ representing a +1 signal

Q phase - $(-\sqrt{3}/2, -1/2, +1/2, +\sqrt{3}/2, +\sqrt{3}/2, +1/2, -1/2, -\sqrt{3}/2, -\sqrt{3}/2, -1/2, +1/2, +\sqrt{3}/2)$ representing a -1 signal.

One skilled in the art will appreciate that the above can be extended to n half cycles of a subcarrier per ranging code chip.

It will be appreciated that other phases can be used to describe the subcarriers. For example, phase and amplitude components of 16-PSK can be used to create BOC16 subcarriers having 9 levels, assuming that the first state is at $(+1,0)$. Using m-PSK phase states can be used to produce $(m+2)/2$

level subcarrier signals. Therefore, setting $m=2$ gives the conventional BPSK and a two-level subcarrier. Setting $m=4$ provides a 3 level subcarrier, that is, BOC4 modulation, setting $m=8$ produces a 5 level subcarrier, that is, BOC8 modulation, setting $m=16$ produces a 9 level subcarrier, which corresponds to BOC16 modulation.

5 It will be appreciated that several further variations in the assignment of code and data states to the phase locations can be realised. For example, rotation of the states shown in figure 4 by 22.5° leads to a reassignment of angles associated with the states from the angles ($0^\circ, 45^\circ, 90^\circ, 135^\circ, 180^\circ, 225^\circ, 270^\circ, 315^\circ$) to the angles ($22.5^\circ, 67.5^\circ, 112.5^\circ, 157.5^\circ, 202.5^\circ, 247.5^\circ, 292.5^\circ, 337.5^\circ$). Again, it will be appreciated that this does not cause a change in the modulus of the spectrum and, again, the
 10 required number of amplitude levels reduces from 5 to 4, that is, m-PSK can be used to realise $[(m+2)/2-1]$ amplitudes according to appropriate rotation and alignment of the phase states. The resulting waveforms for the I and Q components are built, in this case, from the following signal element sequences:

I phase - $(+\cos(67.5^\circ), +\cos(22.5^\circ), +\cos(22.5^\circ), +\cos(67.5^\circ))$ representing a +1 signal

15 I phase - $(-\cos(67.5^\circ), -\cos(22.5^\circ), -\cos(22.5^\circ), -\cos(67.5^\circ))$ representing a -1 signal

Q phase - $(+\sin(67.5^\circ), +\sin(22.5^\circ), -\sin(22.5^\circ), -\sin(67.5^\circ))$ representing a +1 signal

Q phase - $(-\sin(67.5^\circ), -\sin(22.5^\circ), +\sin(22.5^\circ), +\sin(67.5^\circ))$ representing a -1 signal.

It should be noted that the I and Q signal element sequences for the cases described above are orthogonal over the duration of one spreading pulse (chip). Clearly, other rotations are possible and
 20 will yield orthogonal signal element sets.

An alternative way of representing the above is via a state table. Assume that an embodiment of a BOC8 modulation has been realised with equidistant states and the first state having a phase angle of $\pi/8$ radians (22.5°) as shown in figure 8, which correspond to the above values. The sequence of phase states required for each I and Q ranging code signal components, assuming that the ranging
 25 codes transition substantially simultaneously and a desire to maintain a substantially constant output envelope, that is, the states for the subcarriers would be given by

I	Q	t1	t2	t3	t4
+1	+1	2	1	8	7
-1	+1	3	4	5	6
+1	-1	7	8	1	2
-1	-1	6	5	4	3

Table 1 – Sequence of States for BOC8(x,x) I & Q signal elements

It will be appreciated that the subcarrier corresponding to the phase states in Table 1 comprises a half cycle per ranging code chip. Furthermore, the sense of the phasor is clockwise when I and Q are equal and anticlockwise otherwise. It will be apparent that the signal element sequences or state sequences are sections (specifically half cycle sections in the aspect of the invention disclosed above) of a sampled or quantised sinusoid. The concept can, therefore, be extended to include a multiplicity of such samples. Those variants, which appear to be useful, include the cases with samples from a finite number of half cycles, that is, rather than, for example, an I channel value of +1 being represented by the states of 2, 1, 8 and 7, it can be represented using some other number of states such as, for example, 2, 1, 8, 7, 6, 5, 4, 3, 2, 1, 8, 7 ie by three half cycles of the sample or quantised sinusoid. Table 2 illustrates the phase states for such an embodiment and is based on the phase state diagram of figure 4 for samples but using three half cycles (or an arbitrary number of half cycles) of the sinusoid waveform. The sinusoid or portion or multiple of half cycles thereof is known as the 'basis waveform'. One skilled in the art realises that other basis waveforms can be used such as, for example, a triangular waveform or a set of mutually orthogonal waveforms.

I	Q	t1	t2	t3	t4	t5	t6	t7	t8	t9	t10	T11	t12
+1	+1	2	1	8	7	6	5	4	3	2	1	8	7
-1	+1	3	4	5	6	7	8	1	2	3	4	5	6
+1	-1	7	8	1	2	3	4	5	6	7	8	1	2
-1	-1	6	5	4	3	2	1	8	7	6	5	4	3

Table 2 – Sequence of States for 8-PSK I & Q Signal Elements with 1½ cycles of sub-carrier per chip modulation

I	Q	t1	t2	t3	t4	t5	t6	t7	t8
+1	+1	2	1	8	7	6	5	4	3
-1	+1	3	4	5	6	7	8	1	2
+1	-1	7	8	1	2	3	4	5	6
-1	-1	6	5	4	3	2	1	8	7

5 Table 3 – Sequence of States for 8-PSK I & Q Signal Elements with two half cycles of sub-carrier per chip modulation.

One skilled in the art will appreciate that it is assumed in Tables 1 to 3, that the I and Q chip transitions happen substantially simultaneously and, furthermore, that the I and Q subcarriers take the form of sine and cosine waveforms respectively. However, embodiments can be realised in which the ranging code chip transitions do not occur substantially simultaneously. Furthermore, in circumstances in which the ranging code chip transitions do not occur substantially simultaneously, the subcarriers corresponding to the I and Q ranging code chips can be arranged to take the form of a pair of quantised sine waves.

It will be seen that there are 4 time samples for each ½ cycle of the waveform. The stepped sinusoidal waveform may be viewed as sub-carrier modulation of the basic spreading waveform. The number of time samples and independent information bearing channels is related to the number of phase states, which the carrier signal has in its representation. Although the examples above have used phase states that are 'powers of 2', embodiments can be realised in which some other number is used. For example, a 6-PSK carrier signal can be used to carry 2 independent information bearing binary channels. In this case only 3 signal element samples are required per transmitted code chip.

One skilled in the art appreciates that the replacement of the stepped sinusoid with a rectangular wave with duration of each element equal to a ½ cycle of the sinusoid is well known within the art. As indicated above, it is known as 'Binary Offset Carrier' modulation. There are usually 2 further attributes associated with the BOC description, which relate to the frequency of the code chipping rate

and to the frequency of the offset sub-carrier. BOC(2,2) consequently is interpreted as a waveform with a 2.046MHz chipping rate and a 2.046MHz offset sub-carrier. This arrangement has exactly two ½ cycles of the sub-carrier signal for each code element (chip).

A further aspect of embodiments of the present invention relates to using a set of subcarriers to modulate ranging codes, with at least one or more, or all, of the subcarriers being multilevel waveforms. One skilled in the art may think of such embodiments as modulation of the subcarrier signal by a further subcarrier signal. The resulting signal transmitted by an *i*th satellite or system having a carrier frequency of ω_i , for an additional subcarrier, would have the form:

$$S_i(t) = A_m sc_{jm}(t) sc_{im}(t) m_i(t) d_i(t) \cos(\omega_i t) + A_c sc_{jg}(t) sc_{ig}(t) g_i(t) d_i(t) \sin(\omega_i t) = I_{Si}(t) + Q_{Si}(t)$$

10 where

$sc_{im}(t)$ and $sc_{jm}(t)$ represent first and second subcarrier signals respectively first ranging codes such as, for example, M-codes; and

$sc_{ig}(t)$ and $sc_{jg}(t)$ represent first and second subcarrier signals second ranging codes such as, for example, Gold codes. In general, for *n* subcarriers, the signal would have the form:

15 It should be noted that embodiments can be realised in which $sc_{im}(t)$ and $sc_{ig}(t)$ are the same or different. Similarly, embodiments can be realised in which $sc_{jm}(t)$ and $sc_{jg}(t)$ are the same or different.

$$S_i(t) = A_m \prod_{j=1}^n sc_{ijm}(t) m_i(t) d_i(t) \cos(\omega_i t) + A_c \prod_{j=1}^l sc_{ijg}(t) g_i(t) d_i(t) \sin(\omega_i t) = I_{Si}(t) + Q_{Si}(t),$$

where $\prod_{j=1}^n sc_{ijm}(t)$ and $\prod_{j=1}^l sc_{ijg}(t)$ represents the product of the subcarriers for the first and second ranging codes such as, for example, the *m* and Gold codes.

20 Although it is possible to use more than one subcarrier, practical embodiments will typically use 2 subcarriers. Modulation using a pair of subcarriers is known as Double Binary Offset Carrier (DBOC) modulation. Modulation using three subcarriers is known as Triple Binary Offset Carrier (TBOC) modulation and so on such that modulation using a *n*-tuple of subcarriers is known as *N*-tuple Binary Offset Carrier (NBOC). As mentioned above, one or more than one of the subcarriers
25 may be stepped, that is, having magnitudes related to respective phase states.

As examples of this aspect of the invention, figure 9 illustrates a pair of waveforms 900. In figure 9, as an illustration of the NBOC invention, the subcarrier basis waveforms are assumed to be binary and only a single subcarrier waveform 902 is shown. The time duration in figure 9 is 512 samples and

exactly matches the duration of one code element duration (chip). The first subcarrier 902 contains 4 half cycles of a subcarrier per ranging code chip, as illustrated by the dashed waveform. If this was the only sub-carrier component, the modulation would be a BOC(2x,x) type, where x is the frequency of the code rate (chipping rate). However, it can be appreciated that a second sub-carrier (not shown) having 16 half cycles per 512 samples has been used to produce the modulated waveform 904 to be combined with the carrier of the satellite signal. The modulated waveform is shown by the solid curve. As a result of modulation (multiplication) of the two subcarriers, the resulting waveform 904 has phase reversals for the second subcarrier 904 whenever there is a sign reversal in the first subcarrier 902. This is clearly evident in figure 9 at points 906, 908 and 910, where the transitions of the second subcarrier (not shown) would have been opposite. The resulting modulation is denoted Double BOC, or DBOC. In the case of figure 9, the modulation is DBOC(8x,(2x,x)), that is, there are 8 half cycles of the second subcarrier per chip of the ranging code (not shown). The main energy is concentrated around frequencies $\pm 8x$ from the carrier signal, with a BOC like double humped spectrum.

Referring to figure 10, there is shown a pair of power spectra 1000. A first power spectrum 1002 relates to a DBOC8(16,(2,2)) signal. It will be appreciated that at least one of the first and second subcarriers used to create the DBOC8(16,(2,2)) signal comprised amplitudes derived from 8 corresponding phase states. In the specific embodiment shown, the first subcarrier was the multi-level signal. It will be appreciated that the nomenclature for representing DBOC modulation or subcarriers is DBOCa(b,c(d,e)), where a and c represent the number of phase states, that is, amplitudes, of the subcarriers having frequencies b and d respectively. The second spectrum 1004 relates to a BOC8(2,2) signal. The spectra shown have been made using a previous aspect of the invention, that is the use of multilevel subcarriers or subcarriers having more than two phase states, in combination with the Double BOC concept. The waveforms for I & Q modulations for the spectrum of figure 10 are shown in figure 11. Referring to figure 11 there is shown a pairs 1100 of waveforms. The first pair of waveforms 1102, representing the I channel of the spreading waveform, comprises a stepped or multi-level BOC(2,2) signal 1104, represented by the solid line, and a 16Mhz subcarrier modulated BOC(2,2) signal 1106, represented by the dashed line. It will be appreciated that the 16 MHz subcarrier modulated BOC(2,2) signal has been produced by multiplying the BOC8(2,2), that is, stepped BOC(2,2) signal, by a 16 MHz rectangular waveform (not shown) having amplitudes of ± 1 . The second waveform 1108, representing the Q channel, comprises a quadrature BOC(2,2) signal 1110 together with a 16MHz subcarrier modulated BOC(2,2) signal 1112. It can be appreciated that the first subcarrier 1104 or 1110 is a subcarrier according to an embodiment of the present invention described above whereas the second sub-carrier (not shown) in both cases are conventional binary rectangular waveforms, that is, conventional subcarriers. It can be appreciated that there are regions 1114 of overlap between the two BOC(2,2) subcarriers 1104 and 1110 and their resulting products,

that is, 16 MHz subcarrier modulated BOC(2,2) signals 1106 and 1112. In the regions of overlap 1114, the waveforms have the same amplitude profile.

5 An advantage of the embodiments of the signals shown in figure 11 is that the I channel or component has been produced or represents DBOC8 modulation or signal whereas the Q channel has been produced using or represents BOC8 modulation. However, this arrangement still preserves or provides a substantially constant envelope carrier signal to be emitted from the satellite.

10 Embodiments of the present invention have been described with reference to the subcarrier signals being periodic. However, embodiments can be realised in which the subcarrier signal comprises a pseudorandom noise signal. Furthermore, embodiments can be realised in which the shape of the subcarrier takes a form other than a stepped, that is, a multilevel wave or quantised approximation of a sinusoidal waveform. For example, multilevel-pulsed waveforms, multilevel-periodic waveforms or multilevel-aperiodic waveforms, could be used such as the signal shown in figure 12 according to the influence one skilled in the art wishes the resulting modulation to have on the power spectrum of the transmitted signal and/or any appropriate measure of interference such as, for example, SSC or self-SSCs.

15 The use of additional sequences to that of the main spreading code has hitherto been limited to use as a tiered code, which changes state after every complete code repetition interval. The GPS L5 codes are constructed in this manner using Neumann Hoffman sequences of length 10 or 20 to extend a 1ms code (of 10230 chips or elements) to 10ms or 20ms. The use of a subcode chip interval has not previously been considered. A complete

20

sequence (a sub-sequence) has a duration of one code chip, or at most a plurality, of code chips. It fulfills a similar role to the sub-carrier modulation as previously described in that it controls the spectrum of the emissions. One feature of such a sub-sequence is that such sequences may be chosen to be common amongst a satellite constellation or a sub-set of the constellation. One such subset
 5 might be a group of ground transmitters providing a local element or augmentation to the space segment of the system. For example, subcarrier amplitudes can be realised that have the sequence -
 +++++-+ in 10 subchip intervals or other sequence of +1's and -1's per ranging code chip or other
 subcarrier chip according to the desired effect on spectrum of the resulting signal. Examples such as
 the 7 subchip interval sequences would include ++---, +++---, +-+---, and can be chosen to
 10 provide similar control over the emitted spectrum.

Referring to figure 13, there is shown, schematically, a transmitter 1400 according to an embodiment of the present invention. The transmitter 1400 comprises means 1402, that is, a generator, for generating or selecting the ranging codes for transmission. It will be appreciated by those skilled in the art that such ranging code may be generated by, for example, shift register implementations. It
 15 can be appreciated that the ranging code selection and/or generation means 1402 is illustrated as producing $g_i(t)$ and $p_i(t)$. These codes are fed to respective mixers 1404 and 1406. The mixers 1404 and 1406 are arranged to combine the ranging codes with subcarriers according to embodiments of the present invention. Respective subcarrier generators 1408 and 1410 generate the subcarriers. Optionally, a data signal, $d_i(t)$, is also preferably mixed with the ranging codes and subcarriers. The
 20 duration of one bit of the data signal is normally an integer multiple of the code repetition interval. For example, in GPS CA code, it is 20 times the 1 ms code repetition interval, that is, the data rate is 50 bps. The mixed signals 1412 and 1414 are fed to a further pair of mixers 1416 and 1418, where they are mixed with in-phase and quadrature phase signals produced via an oscillator and phase shifter assembly 1420. The further mixed signals 1422 and 1424 are combined, via a combiner 1426, and
 25 output for subsequent up conversion by an appropriate up converter 1428. The output from the up converter 1428 is fed to a high-power amplifier 1430 and then filtered by an appropriate filter 1433 for subsequent transmission by, for example, a satellite or other device arranged to emit or transmit the ranging codes.

Referring to figure 14, there is shown a schematic representation of a modulation system 1500 according to an embodiment. The system 1500 comprises a ranging code generator 1502 for producing a ranging code. The ranging code is fed to a first lookup table 1504 comprising phase states and a second lookup table 1506 comprising amplitude states. The output of the phase state
 30 lookup table 1504 is used to drive a phase modulator 1508, which, in turn, produces a voltage signal to control the phase of a voltage controlled oscillator 1510. The output of the oscillator 1510 is combined, via, a combiner 1512 such as, for example, a gain controlled amplifier or multiplier, with a
 35

signal output from the amplitude state table 1506 to produce a subcarrier having the appropriate characteristics.

Although the above embodiments have been described with reference to maintaining a substantially constant signal envelope, embodiments are not limited thereto. Embodiments can be realised in which variable modulus signal envelopes are used. It will be appreciated that the constraints described above, which are aimed at preserving unitary magnitude of $(I^2+Q^2)^{1/2}$, need not necessary apply.

The above embodiments have been described with reference to the I and Q channels having the same chipping rates. However, embodiments are not limited to such arrangements. Embodiments can be realised in which different chipping rates are used.

Although embodiments of the present invention have been described with reference to the L1 and L2 frequencies, embodiments are not limited to such arrangements. Embodiments can be realised in which other frequencies or frequency bands can be used according to the requirements of the system using the invention. For example, the lower L band (ie E5a and E5b), the middle (ie E6) and upper L-band (ie E2-L1-E1) can also benefit from embodiments of the present invention. It will be appreciated that such embodiments may use signals having at least three components rather than the two components described above.

Furthermore, embodiments of the present invention have been described with reference to standard BOC. However, one skilled in the art appreciated that embodiments can also be realised using Alternative BOC.

Furthermore, it will be appreciated that embodiments can be realised in which the number of half cycles of a subcarrier per chip of a code can be at least one of odd, even, an integer multiple or a non-integer multiple of the chip, that is, there is a rational number relationship between the number of subcarrier half cycles and the chip duration.

Embodiments of the present invention described above have focused on the transmission side of the invention, that is, upon the generation, modulation and transmission of ranging codes combined with a subcarrier or subcarriers. However, one skilled in the art appreciated that a converse system and method are required to receive and process the signals. Once one skilled in the art has designed a system for transmitting such signals, designing an appropriate receiver is merely the converse of the transmit operations. Therefore, embodiments of the present invention also relate to a receiver for processing signals such as those described above.

All of the features disclosed in this specification (including any accompanying claims, abstract and drawings), and/or all of the steps of any method or process so disclosed, may be combined in any combination, except combinations where at least some of such features and/or steps are mutually exclusive.

- 5 Each feature disclosed in this specification (including any accompanying claims, abstract and drawings) may be replaced by alternative features serving the same, equivalent or similar purpose, unless expressly stated otherwise. Thus, unless expressly stated otherwise, each feature disclosed is one example only of a generic series of equivalent or similar features.

The invention is not restricted to the details of any foregoing embodiments. The invention
10 extends to any novel one, or any novel combination, of the features disclosed in this specification (including any accompanying claims, abstract and drawings), or to any novel one, or any novel combination, of the steps of any method or process so disclosed.

CLAIMS:

1. A method of generating a navigation transmission signal in a navigation system comprising a carrier signal, a ranging code, a data signal and at least one subcarrier modulation signal, the method comprising the step of modulating the carrier signal by the at least one subcarrier modulation signal, the data signal and the ranging code to generate the navigation transmission signal; wherein the at least one subcarrier modulation signal comprises a number, m , of amplitude levels, where $m > 2$.
2. The method as claimed in claim 1 comprising the step of creating the at least one subcarrier modulation signal having m amplitudes, where $m > 2$.
3. The method as claimed in claim 1 or 2 in which m is selected from at least one of 3, 4, 5, 6, 7, 8 and 9.
4. The method as claimed in any one of claims 1 to 3 in which the at least one subcarrier modulation signal approximates or is derived from a predeterminable basis waveform.
5. The method as claimed in claim 4 in which the basis waveform is at least one of a sine wave, cosine wave and triangular waveform.
6. The method as claimed in claim 4 or 5 in which the basis waveform is selected according to desired power distribution characteristics of the navigation transmission signal.
7. The method as claimed in any one of claims 1 to 6 in which the at least one subcarrier modulation signal comprises at least two subcarrier modulation signals that are mutually orthogonal.
8. The method as claimed in claim 7 in which the at least two subcarrier modulation signals comprises a pair of subcarriers having a predetermined phase relationship.

9. The method as claimed in any one of claims 1 to 8 in which the at least one subcarrier modulation signal comprises an in-phase subcarrier and a quadrature phase subcarrier.
10. The method as claimed in claim 9 further comprising the step of determining the respective multiple amplitudes of the in-phase and quadrature phase subcarriers to maintain a substantially constant navigation transmission signal envelope.
11. The method as claimed in any one of claims 1 to 10 further comprising the steps of deriving the amplitudes associated with the at least one subcarrier modulation signal from a plurality of phase states.
12. The method as claimed in claim 11, in which the phase states are equally angularly distributed around a unit circle.
13. The method as claimed in any one of claims 1 to 12 in which durations of the amplitudes of the at least one subcarrier modulation signal are substantially equal.
14. The method as claimed in any one of claims 1 to 13 in which the durations of at least a pair of amplitudes of the at least one subcarrier modulation signal are different.
15. The method as claimed in any one of claims 1 to 14 in which the durations are quantised according to an associated clock signal.
16. The method as claimed in any one of claims 1 to 15 in which at least a pair of subcarrier modulation signals cooperate to define an associated plurality of phase states resolved according to mutually orthogonal axes.
17. The method as claimed in claim 16 in which the plurality of phase states is associated with respective ranging signals.

18. The method as claimed in claim 16 or 17 in which dwell times in at least some of the plurality of phase states are unequal.
19. The method as claimed in any one of claims 16 to 18 in which a first group of the phase states have a first dwell time and a second group of the phase states have a second dwell time.
20. The method as claimed in any one of claims 16 to 19 in which the dwell times are quantised according to a clock.
21. A ranging system comprising: means for generating a ranging code; means for generating a carrier signal; means for generating at least one subcarrier modulation signal; means for generating a data signal; and means for combining the ranging code, the carrier signal, the at least one subcarrier modulation signal and the data signal to produce a navigation transmission signal; wherein
the means for generating the at least one subcarrier modulation signal comprises means for generating said at least one subcarrier modulation signal comprising a number, m , of amplitude levels, where $m > 2$.
22. The ranging system as claimed in claim 21 wherein the means for generating the at least one modulation signal comprises means for creating the at least one subcarrier modulation signal having m amplitudes, where $m > 2$.
23. The ranging system as claimed in claim 21 or 22 in which m is selected from at least one of 3, 4, 5, 6, 7, 8 and 9.
24. The ranging system as claimed in any one of claims 21 to 23 in which at least one subcarrier modulation signal approximates or is derived from a predeterminable basis waveform.

25. The ranging system as claimed in claim 24 in which the basis waveform is at least one of a sine wave, cosine wave and triangular waveform.
26. The ranging system as claimed in claim 24 or 25 in which the basis waveform is selected according to desired power distribution characteristics of the navigation transmission signal.
27. The ranging system as claimed in any one of claims 21 to 26 in which at least two of the subcarrier modulation signals are mutually orthogonal.
28. The ranging system as claimed in any one of claims 21 to 27 in which the plurality of subcarrier modulation signals are mutually orthogonal.
29. The ranging system as claimed in any one of claims 21 to 28 in which the plurality of subcarrier modulation signals comprises a pair of subcarriers having a predetermined phase relationship.
30. The ranging system as claimed in any one of claims 21 to 29 in which the plurality of subcarrier modulation signals comprises an in-phase subcarrier and a quadrature phase subcarrier.
31. The ranging system as claimed in claim 30 further comprising means for determining the respective multiple amplitudes of the in-phase and quadrature phase subcarriers to maintain a substantially constant navigation transmission signal envelope.
32. The ranging system as claimed in any one of claims 21 to 31 further comprising means for deriving the amplitudes associated with at least a pair of orthogonal subcarriers from a plurality of phase states.
33. The ranging system as claimed in claim 32 in which the phase states are equally angularly distributed around a unit circle.

34. The ranging system as claimed in any one of claims 21 to 33 in which durations of the amplitudes of the at least one subcarrier modulation signal are substantially equal.
35. The ranging system as claimed in any one of claims 21 to 33 in which the durations of the at least a pair of amplitudes of at least one subcarrier modulation signal are different.
36. The ranging system as claimed in any one of claims 21 to 33 in which the durations are quantised according to an associated clock signal.
37. The ranging system as claimed in any one of claims 21 to 36 in which at least a pair of the at least one subcarrier modulation signals cooperate to define an associated plurality of phase states resolved according to mutually orthogonal axes.
38. The ranging system as claimed in claim 37 in which the plurality of phase states is associated with respective ranging signals.
39. The ranging system as claimed in claim 37 or 38 in which dwell times in at least some of the plurality of phase states are unequal.
40. The ranging system as claimed in any one of claims 37 to 39 in which a first group of the phase states have a first dwell and a second group of the phase states have a second dwell time.
41. The ranging system as claimed in any one of claims 37 to 40 in which the dwell times are quantised according to a clock.
42. A receiver for processing a navigation transmission signal; the navigation transmission signal comprising a carrier signal, and at least one ranging code modulated by at least one subcarrier modulation signal, a data signal; the at least one subcarrier modulation signal comprising a number, m , of amplitude levels, where $m > 2$;
the receiver comprising:

means to receive the navigation transmission signal;

means to process the navigation transmission signal to recover the modulated at least one ranging code, and

means to process the recovered at least one modulated ranging code to recover at least one demodulated ranging code.

43. A method of processing a navigation transmission signal; the navigation transmission signal comprising a carrier signal, and at least one ranging code modulated by at least one subcarrier modulation signal, a data signal; the at least one subcarrier modulation signal comprising a number, m , of amplitude levels, where $m > 2$;

the method comprising the steps of

receiving the navigation transmission signal;

processing the navigation transmission signal to recover the modulated at least one ranging code, and

processing the recovered at least one modulated ranging code to recover at least one demodulated ranging code.

44. The receiver or method as claimed in one of claims 42 or 43, wherein at least one of the first and second BOC subcarriers comprises m discrete amplitude levels, where $m > 2$.

45. The receiver or method as claimed in claim 44, wherein m is selected from at least one of 3, 4, 5, 6, 7, 8 or 9.

46. The receiver or method as claimed in either of claims 44 and 45 in which at least one of the subcarrier modulation signals approximates or is derived from a predeterminable basis waveform.

47. The receiver or method as claimed in claim 46 in which the basis waveform is at least one of a sine wave, cosine wave, triangular waveform.

48. The receiver or method as claimed in either of claims 46 and 47 in which the basis waveform is selected according to desired power distribution characteristics of the navigation transmission signal.
49. The receiver or method as claimed in any one of claims 42 to 48 which the at least one subcarrier modulation signal comprises at least two subcarrier modulation signals that are mutually orthogonal.
50. The receiver or method as claimed in any one of claims 1 to 49 further comprising the steps of deriving the amplitudes associated with said at least one subcarrier modulation signal from a plural of phase states.
51. The receiver or method as claimed in claim 50, in which the phase states are equally angularly distributed around a unit circle.
52. The receiver or method as claimed in any of claims 42 to 51 in which durations of the amplitudes of the at least one subcarrier modulation signal are substantially equal.
53. The receiver or method as claimed in any of claims 42 to 51 in which the durations of at least a pair of amplitudes of the at least one subcarrier modulation signal are different.
54. The receiver or method as claimed in any of claims 42 to 53 in which the durations are quantised according to an associated clock signal.
55. The receiver or method as claimed in any one of claims 42 to 54 in which said at least one subcarrier modulation signal comprises at least a pair of subcarriers cooperate to define an associated plural of phase states resolved according to mutually orthogonal axes.
56. The receiver or method as claimed in claim 55 in which the plurality of phase states is associated with respective ranging signals.

57. The receiver or method as claimed in either of claims 55 and 56, in which dwell times in at least some of the plurality of phase states are unequal.

58. The receiver or method as claimed in any of claims 55 to 57 in which a first group of the phase states have a first dwell time and a second group of the phase states have a second dwell time.

59. The receiver or method as claimed in any of claims 55 to 58 in which the dwell times are quantised according to a clock.

60. A computer readable storage medium comprising computer executable code for implementing the method as claimed in any one of claims 1 to 20 or any one of claims 43 to 59.

Figure 1




Figure 2




Figure 3




Figure 4




Figure 5




Figure 6




Figure 7a




Figure 7b




Figure 8




Figure 9





Figure 10







Figure 11






Figure 13




Figure 14




Figure 15

