



(19) **United States**

(12) **Patent Application Publication**  
**Birleson et al.**

(10) **Pub. No.: US 2007/0182866 A1**

(43) **Pub. Date: Aug. 9, 2007**

(54) **HIGHLY INTEGRATED TELEVISION TUNER ON A SINGLE MICROCIRCUIT**

No. 09/572,393, filed on May 16, 2000, now Pat. No. 7,079,195, which is a continuation of application No. 08/904,908, filed on Aug. 1, 1997, now Pat. No. 6,177,964.

(75) Inventors: **S. Vincent Birleson**, West Tawakoni, TX (US); **Robert R. Rotzoll**, Cascade, CO (US); **Albert H. Taddiken**, Garland, TX (US); **Kenneth W. Clayton**, Plano, TX (US)

Said application No. 11/376,745 is a continuation-in-part of application No. 08/426,080, filed on Apr. 21, 1995, now Pat. No. 5,737,035.

**Publication Classification**

(51) **Int. Cl.**  
**H04N 5/44** (2006.01)  
(52) **U.S. Cl.** ..... **348/725**

Correspondence Address:  
**FULBRIGHT & JAWORSKI L.L.P**  
**2200 ROSS AVENUE**  
**SUITE 2800**  
**DALLAS, TX 75201-2784 (US)**

(73) Assignee: **Microtune (Texas), L.P.**, Plano, TX

(57) **ABSTRACT**


(21) Appl. No.: **11/735,825**

A broadband integrated receiver for receiving input signals and outputting composite video and audio signals is disclosed. The receiver employs an up-conversion mixer and a down-conversion mixer in series to produce an intermediate signal. An intermediate filter between the mixers performs coarse channel selection. The down-conversion mixer may be an image rejection mixer to provide additional filtering.

(22) Filed: **Apr. 16, 2007**

**Related U.S. Application Data**

(63) Continuation of application No. 11/376,745, filed on Mar. 15, 2006, which is a continuation of application










FIG. 2

FIG. 3





## HIGHLY INTEGRATED TELEVISION TUNER ON A SINGLE MICROCIRCUIT

### RELATED APPLICATIONS

[0001] This application is a continuation of co-pending application entitled BROADBAND INTEGRATED TUNER assigned Ser. No. 08/904,908, and is related to co-pending application entitled DUAL MODE TUNER FOR CO-EXISTING DIGITAL AND ANALOG TELEVISION SIGNALS assigned Ser. No. 08/904,693, and co-pending application entitled BROADBAND FREQUENCY SYNTHESIZER assigned Ser. No. 08/904,907, all of which are assigned to a common assignee, which applications are hereby incorporated by reference herein.

### TECHNICAL FIELD OF THE INVENTION

[0002] This invention relates to television tuner circuits and more particularly to a broadband analog television tuner fabricated in a microcircuit device.

### BACKGROUND OF THE INVENTION

[0003] One of the most significant costs in television manufacturing is the cost of the tuner. The typical cost of a television (TV) tuner is in the neighborhood of \$15.00, which, relative to the cost of the entire television set, is very substantial. Part of the solution to reducing tuner cost is to reduce the number of components in the tuner.

[0004] Traditionally, tuners have been comprised of two basic components. The first component performs high frequency to intermediate frequency (RF to IF) conversion. Subsequently, the second component performs IF to baseband conversion. The TV tuner was originally designed for broadcast television reception within a television set, which is essentially a stand-alone unit containing a cathode ray picture tube. So, TV tuners were originally integral parts embedded in a single-purpose device.

[0005] Presently, however, state-of-the-art consumer electronic devices use TV tuners that are not a built-in part of a television set. The tuner is a separate element that is connected to a cathode ray picture tube at some point, but the tuner is not an integral part of the monitor. For example, TV tuners may be fabricated on circuit boards and then installed in personal computer (PC) systems, thereby allowing the PC to function as a television set. These tuners convert a radio frequency television signal into a baseband (or low frequency) video signal which can then be passed on to other elements in the PC for video processing applications.

[0006] The circuit component that performs the RF-to-IF conversion typically comprises one or two integrated circuits and numerous discrete elements—inductors, capacitors and/or transistors. The IF-to-baseband conversion typically includes another integrated circuit, several filter elements, such as ceramic filters and SAW filters, a series of tuning and control elements, such as resistors and potentiometers, variable inductors and/or capacitors, and some other additional external components. Thus, the complexity of the tuner is fairly high and typically there may be between 100 and 200 elements on a circuit board. Furthermore, state-of-the-art TV tuners still require that each tuner be aligned by manual tuning before leaving the factory. This manual tuning is one of the most expensive costs associated with the manufacturing process and an important factor in the cost of tuners.

[0007] Broadcast television tuners of the past have gone through an evolution over a period of more than 60 years. The earliest tuners utilized vacuum tube technology and required that the minimum number of vacuum tubes possible be used due to their cost, power consumption and dimensions. Therefore, passive components, such as resistors, capacitors, inductors and transformers, were used as much as possible in most designs. This style of design continued until about 1960 when TV tuner components, particularly vacuum tubes, began to be replaced by bipolar and MOS transistors. However, the active device count still defined the cost and size limits of TV tuners and active device count minimization continued.

[0008] In the early 1970's the integrated circuit became viable as an element in the television tuner and the design techniques were dramatically changed. Many functions of the tuner utilizing only one tube or transistor were being replaced with 4 to 20 individual transistors which could perform the same function with better precision, less space, less power, less heat generation and lower cost. The introduction of the integrated circuit was gradual, first encompassing only low frequency elements and then eventually high frequency active elements. Nonetheless, many passive elements external to the integrated circuits remained in TV tuner designs.

[0009] One advance, the SAW (surface acoustic wave) filter, made a significant change in that several manually tuned inductors and capacitors could be removed from the tuners and receive-filtering performance could be improved within a much smaller space and at reduced cost. However, the SAW filter, which is fabricated on a ceramic substrate, cannot be integrated on a silicon wafer with the rest of the active circuitry and must therefore remain a discrete component in the final design. The trend of the 1980's was to miniaturize all of the passive components and simplify their associated manual tuning at the factory. In recent years, TV tuners have been reduced in size from requiring fairly large enclosures, about 2"x5"x1", to much smaller enclosures, about 1/2"x2"x3/8". There is a high premium placed on small size because TV tuners are being used in smaller and smaller computers, television sets and VCRs. As the equipment in which tuners are used becomes smaller, the size of the TV tuner must decrease also.

[0010] As the size of the tuner goes down, and as tuners are used in a wider variety of devices, cost becomes more critical and must be reduced as much as possible in order not to represent a large portion of the final product cost. When a timer is used in a television set, the tuner size is less critical because the television set inherently has a large mass. But when a tuner is used in other electronic equipment, space becomes a premium and the footprint of the tuner becomes critical.

[0011] Accordingly, it is one object of the invention to provide a TV tuner which has a relatively low cost and a small footprint for use on a printed circuit board.

[0012] It is another object of the present invention to provide a TV tuner that meets or exceeds the performance of state-of-the-art TV tuners while at the same time reducing the number of external components needed, thereby decreasing the complexity of the printed circuit board and the amount of circuit board area needed by the TV tuner.

[0013] It is the further object of the present invention to allow for computer control of the TV tuner by a serial bus

so that the TV tuner may be controlled by a microcontroller imbedded in the television set, personal computer, or other video device.

[0014] It is the further object of the present invention to provide a TV tuner with computer-controlled output impedance characteristics to accommodate different load specifications.

#### SUMMARY OF THE INVENTION

[0015] These and other problems have been solved by a television tuner that receives a broad band of RF signals and converts a desired RF television channel to an IF signal having a picture carrier at 45.75 MHz. To accomplish this, an architecture was chosen to perform an up-conversion of the RF input signal to a higher internal frequency, which allows the present invention to have minimal filtering on the input stages of the receiver. The present invention is therefore able to operate without variable-tuned input filtering. This eliminates the need for precisely controlled variable tuned filters which must be mechanically aligned during manufacture and are subject to variation in performance due to age, temperature, humidity, vibration and power supply performance. This was a critical drawback of previous tuners that had to be eliminated because it is a source of tremendous error and distortion, as well as complexity.

[0016] The present invention allows a wide band of frequencies to enter the front end of the tuner circuit without removing frequencies in an input band pass tracking filter. An input filter allows RF signals, typically in the range from 55-806 MHz, to enter the circuit while rejecting high frequency signals above the television band. The input signal then passes through a low noise amplifier that controls the input signal level. Following the input filter and amplifier, the RF signal is converted to an IF signal in a dual mixer conversion circuit. The conversion circuit generally up-converts the RF to a first IF signal and then down-converts the first IF signal to a second IF signal having a 45.75 MHz picture carrier.

[0017] It is advantageous to have the up-conversion performed on-chip to avoid drive capability problems associated with high frequency signals and noise coupling problems resulting from integrated circuit external interconnections. Following the up-conversion, a first IF band pass filter performs coarse channel selection. The present invention next performs a down-conversion on the output of the first IF filter. The down-conversion may be accomplished by an image rejection mixing scheme that provides for a higher level of image rejection than that provided solely by the first IF filter. The use of an image rejection mixer for down-converting the first IF signal is optional depending upon the characteristics of the first IF filter and its ability to reject unwanted signals.

[0018] The present invention advantageously utilizes much less board space than previous designs (on the order of 5% to 10% of the prior art designs) and has the potential to dissipate less power. The present invention also advantageously operates on a single voltage level, as opposed to two or three levels for previous designs.

[0019] A further technical advantage of the present invention is that the need for a metal enclosure is reduced. Integration, by itself, allows for sufficient shielding to meet

interference standards. The monolithic television (MTV) tuner embodied in the present invention is intended to replace the TV tuner modules presently used in most broadcast television receiver devices. The level of integration of the present invention dramatically reduces the cost of the basic TV tuner and enhances its manufacturability and reliability. The TV tuner of the present invention is controlled externally by a computer or controller via a digital serial bus interface, such as the (PC) bus defined by Philips Electronics N.V. A preferred embodiment of the present invention provides an antenna input capable of being connected directly to a standard coaxial cable, thereby allowing both antenna and cable television applications.

[0020] A preferred embodiment of the present invention is designed to operate on frequencies used for both over-the-air broadcasts and cable television with National Television Standards Committee (NTSC) encoded video. Receiver sensitivity is set to be limited by the antenna noise temperature for VHF systems. The present invention also employs a wide-range automatic gain control (AGC).

[0021] For analog television signals, the baseband video output of the present invention is leveled, or has minimal variation in video amplitude with respect to antenna RF signal level. Audio output is broadband composite to allow connection to an external MTS decoder.

[0022] Control is accomplished via a digital service bus interface. The bias and control circuits in a preferred embodiment of the present invention contain internal registers which can be updated via the control bus in response to changes in operating frequency, transmission standards such as NTSC, PAL, SECAM and MTS, power, and test modes. Status of the bias and control circuits can be checked via a status register accessible through the I<sup>2</sup>C bus interface. Status data include AFC error, channel lock and received signal strength indicator.

[0023] The operating frequency of the present invention is referenced to an external crystal or reference frequency generator. A minimum of external components are used in one embodiment of the present invention to reduce the need for tuning of any components.

[0024] The present invention may be implemented in Bipolar, BiCMOS, or CMOS processes. However, a preferred embodiment of the present invention employs a BiCMOS process to reduce the difficulty in developing the design by allowing maximum flexibility.

[0025] In the preferred embodiment, the present invention would be constructed entirely on a single integrated substrate. However, design, manufacturing and cost considerations may require that certain elements be embodied as discrete off-chip devices.

[0026] The foregoing has outlined rather broadly the features and technical advantages of the present invention in order that the detailed description of the integrated television tuner that follows may be better understood. Additional features and advantages of the monolithic television tuner will be described hereinafter which form the subject of the claims of the invention. It should be appreciated by those skilled in the art that the conception and the specific embodiment disclosed may be readily utilized as a basis for modifying or designing other structures for carrying out the same purposes of the present invention. It should also be realized

by those skilled in the art that such equivalent constructions do not depart from the spirit and scope of the invention as set forth in the appended claims.

#### BRIEF DESCRIPTION OF THE DRAWINGS

[0027] For a more complete understanding of the present invention, and the advantages thereof, reference is now made to the following descriptions taken in conjunction with the accompanying drawings, in which:

[0028] FIG. 1 is a detailed block diagram of the present invention;

[0029] FIG. 2 shows the multiple phase lock loop circuit for creating the LO reference signals;

[0030] FIG. 3 is a detailed diagram of the phase lock loop circuit; and

[0031] FIG. 4 is a detailed block diagram of a state-of-the-art television tuner found in the prior art.

#### DESCRIPTION OF THE PRIOR ART

[0032] Before discussing the monolithic television tuner of the present invention, it will be useful to discuss a state-of-the-art television tuner found in the prior art.

[0033] While there have been theoretical proposals to integrate TV tuners in a single microcircuit, none are known to have been implemented. The next best definition of the known prior art, then, is a highly miniaturized, but not fully integrated, tuner as shown in FIG. 4.

[0034] FIG. 4 depicts a functional electrical block diagram of a present state-of-the-art TV tuner configuration. Television tuner 400 is constructed in a single metallic shielded assembly containing a printed circuit board on which all of the associated tuner components are mounted and electrically connected. TV tuner 400 is designed to be a module mounted on other printed circuit boards to allow for direct connection of the input and output signals to their appropriate terminations within the television receiving system. The metal shield is used to keep undesired external signals from interfering with the operation of the TV tuner 400 and to prevent TV tuner 400 from radiating signals that interfere with the operation of external devices.

[0035] Prior art television tuner 400 is comprised of three integrated circuits: preamplifier and mixer 405, IF and baseband signal processor 410 and frequency synthesizer and Inter Integrated Circuit (IIC or I<sup>2</sup>C) bus interface 415. Television tuner 400 is also comprised of a plurality of discrete components, including bandpass and image reject notch filter 404, bandpass and image reject notch filter 412, surface acoustic wave (SAW) filter 416, video carrier filter 424, and audio carrier phase shifter 460.

[0036] Television tuner 400 receives a standard television RF signal from either antenna 402 or a cable system connection (not shown) through bandpass and image reject notch filter 404. Bandpass and image reject notch filter 404 limits the signals entering TV tuner 400 so that a minimum number of undesired signals exist in TV tuner 400. Filter 404 therefore limits the image response caused by the first mixer, described later. Filter 404 also attenuates signals not in a fairly narrow (100 MHz) range about the desired signal. Finally, known interference signals, such as FM broadcast,

shortwave service signals, signals in the intermediate frequency band and Citizen Band radio signals, are specifically rejected by filter 404.

[0037] Preamplifier 406 of preamplifier and mixer 405 receives the output of bandpass and image reject notch filter 404 and raises the signal level (10 dB) with minimum increase in the noise level (typically 8-10 dB). The gain of preamplifier 406 is controlled by automatic gain control (AGC) 438, so that when a very strong signal enters TV tuner 400, overall gain is reduced, resulting in less distortion in the preamplifier than without the gain reduction.

[0038] The output of preamplifier 406 is sent to bandpass and image reject notch filter 412, with the same basic requirement of minimizing the passage of potential interference signals. Filter 412 is external to preamplifier and mixer 405 and is comprised of a plurality of discrete elements, including capacitors, inductors and varactor diodes.

[0039] The output of bandpass and image reject notch filter 412 is then sent back to mixer 408 in preamplifier and mixer 405. Mixer 408 mixes the output of filter 412 with the output of a local oscillator, frequency synthesizer 442, which has a frequency chosen to be higher than the desired receiver carrier by 45.75 MHz. Thus, the output of mixer 408 is 45.75 MHz. There also is an image signal due to mixer 408 at 91.5 MHz above the input frequency, which is removed by filter 404 and filter 412. Therefore, as the frequency of frequency synthesizer 442 is tuned to receive signals of different carrier frequencies, the bandpass and image reject filters 404 and 412 must also be tuned to properly pass only the desired signals and not the mixer images.

[0040] Frequency synthesizer 442 receives an input frequency reference signal (usually 16 bits) and outputs the status signals AUTOMATIC FREQUENCY CONTROL (AFC) ERROR and FREQUENCY (FREQ) LOCK. Additionally, a tuning signal which is used by the voltage controlled oscillator (VCO) in frequency synthesizer 442 is output from frequency synthesizer 442 to bandpass and image reject notch filters 404 and 412. A local oscillator signal is output from frequency synthesizer 442 to mixer 408.

[0041] The 45.75 MHz output signal of mixer 408 then passes through SAW (surface acoustic wave) filter 416, which limits the bandwidth of the signal to only one (1) channel (6 MHz for NTSC standard) and applies a linear attenuation in frequency known as the Nyquist slope around the visual carrier frequency. The linear attenuation by SAW filter 416 converts the signal from a vestigial sideband signal to one which is equivalent to a single sideband with a carrier, so that the frequency response of the signal after demodulation is flat over the video bandwidth. SAW filter 416 is very "lossy" (on the order of 25 dB), so the input to SAW filter 416 is amplified by a preamplifier (not shown) by a corresponding amount to minimize noise effects.

[0042] The output of SAW filter 416 is input to intermediate frequency (IF) amplifier 420 in IF and baseband signal processor 410. IF amplifier 420 provides most of the overall gain of TV tuner 400 and receives gain control from AGC 448.

[0043] The output of IF amplifier 420 is sent to video detector 422 and is also sent off-chip to external video carrier filter 424. This is the stage at which video demodu-

lation is performed. Video detector **422** is essentially a mixer with the local oscillator input connected to the output of video carrier filter **424** through carrier amplitude limiter **426**. The output of the carrier limiter **426** is an in-phase representation of the video carrier signal without any modulation applied to it. The output of carrier limiter **426** is received by video detector **422**, which mixes the output of carrier limiter **426** with the output of IF amplifier **420**.

[0044] AFC frequency discriminator **440** is used in the prior art device to detect the difference between the carrier frequency contained in the output of carrier limiter **426** and a known valid carrier frequency reference. The output signal on the output of AFC frequency discriminator **440** is an error signal which is used to drive frequency synthesizer **442** in a direction that will reduce the error between the output of carrier limiter **426** and the known valid carrier frequency reference. The output of the video detector **422** is a baseband video signal combined with several high frequency mixing artifacts. These artifacts are removed by a video baseband filter **430**. The output of video baseband filter **430** is fed to synchronization pulse clamp (sync clamp) **432**, which sets the level of the sync pulses to a standard level.

[0045] Next, the output of sync clamp **432** is sent to noise inverter **434**, which removes large noise spikes from the signal. The output of noise inverter **434** is sent to video buffer **436**, which is configured to drive fairly high circuit board impedances of approximately 1000 to 2000 ohms.

[0046] The output of noise inverter **434** is also sent to AGC (automatic gain control) **438**, which compares the level of the synchronization pulses to the signal blanking level to measure the incoming signal strength and generates a gain control signal which is used by IF amplifier **420** and RF preamplifier **406** to dynamically adjust the gain of the TV tuner **400** for the correct level at the final output.

[0047] The audio signal is an FM signal which follows the same path as the video through video detector **422**. At the output of video detector **422**, the audio signal appears as a subcarrier at 4.5 MHz, due to the fact that the audio signal comes into prior art TV tuner **400** 4.5 MHz higher in frequency than the desired video carrier. The audio subcarrier is passed on to an FM quadrature demodulator. The FM quadrature demodulator is comprised of a mixer, audio second detector **450**, and a 90 degree (at 4.5 MHz) phase shifter, audio carrier phase shifter **460**. The output of the audio second detector **450** is a baseband audio signal, which is filtered by lowpass (30 kHz) filter **452** to remove any undesired high frequency components. The output of lowpass filter **452** is finally passed on to audio buffer **454**, which drives an audio amplifier that ultimately drives a speaker. Serial digital interface **444** receives SERIAL DATA and SERIAL CLOCK inputs to provide control and update status for the prior art television receiver.

[0048] Baseband and image reject notch filters **404** and **412** are typically comprised of a plurality of capacitors, inductors and varactor diodes. Video carrier filter **424** is usually comprised of three discrete elements: an inductor and two capacitors. Likewise, audio carrier phase shifter **460** is also comprised of an inductor and two capacitors. In addition to the circuit elements shown as discrete components outside of circuit elements **405**, **410** and **415** in FIG. 4, other discrete components (not shown) are connected to IF and baseband signal processor **410** and frequency syn-

thesizer **442** for tuning purposes. Frequency synthesizer **442** is typically tuned by several external capacitors, inductors and/or varactor diodes. Video buffer **436** and audio buffer **454** will also typically employ external discrete elements, such as resistors, capacitors and/or transistors. Video baseband filter **430** and low pass filter **452** may also employ external inductors and capacitors.

#### DETAILED DESCRIPTION OF THE INVENTION

[0049] Turning now to FIG. 1, the preferred embodiment of the present invention is shown as broadband television tuner **10**. The operation of the IF signal processing components of tuner **10** is further disclosed in the above-referenced co-pending applications entitled DUAL MODE TUNER FOR CO-EXISTING DIGITAL AND ANALOG TELEVISION SIGNALS, and INTERFERENCE-FREE BROADBAND TELEVISION TUNER and BROADBAND FREQUENCY SYNTHESIZER. RF signals are received in tuner **10** through input filter **101** which has a high dynamic range and good linearity across the television frequency band. Filter **101** operates to attenuate signals above an input cutoff frequency corresponding to the highest frequency in the television band. As distinguished from the prior art, filter **10** is not a narrow band pass tracking filter which attenuates most television channels from the received signal. Instead, filter **101** passes all channels in the television band.

[0050] Following filter **101**, the RF signal passes through delayed AGC amplifier **102** which operates in conjunction with IF AGC amplifier **116** to control the overall signal level in tuner **10**. Amplifier **102** may be a variable gain amplifier or a variable gain attenuator in series with a fixed gain amplifier. The preferred embodiment of amplifier **102** comprises a low noise amplifier (LNA) with a high linearity that is sufficient to pass the entire television band. Amplifier **102** functions to control high input signal levels in the received RF signal. Tuner **10** is capable of receiving signals from a variety of sources, such as an antenna or a cable television line. The cable television signals may have a signal strength of +15 dBmV and may comprise 100 cable channels. Amplifier **102** regulates the varying signal levels in this broad band of received channels.

[0051] Mixer **103** receives inputs from amplifier **102** and local oscillator **104**. A first IF signal is generated in mixer **103** and provided to first IF filter **109**. Filter **109** is a band pass filter that provides coarse channel selection in tuner **10**. As a matter of design choice, filter **109** may be constructed on the same integrated circuit substrate as mixers **103** and **110** or filter **109** may be a discrete off-chip device. Filter **109** selects a narrow band of channels or even a single channel from the television signals in the first IF signal.

[0052] Following IF filter **109**, mixer **110** mixes the first IF signal with a second local oscillator signal from local oscillator **111** to generate a second IF signal. Mixer **110** may be an image rejection mixer, if necessary, to reject unwanted image signals. The characteristics of first IF filter **109** will determine whether mixer **110** must provide image rejection. If the image frequencies of the desired channel are adequately attenuated by first IF filter **109**, then mixer **110** may be a standard mixer.

[0053] Local oscillators **104** and **111** are controlled by tuning phase locked loop circuit **105**. In the preferred

embodiment, the local oscillator frequencies are selected so that the picture carrier of a particular channel in the RF signal will appear at 45.75 MHz in the second IF signal. However, it will be understood that the present invention is not limited to specific IF or LO frequencies. Tuning PLL circuit **105** receives reference signals from reference oscillator **106** which is driven by 5.25 MHz crystal **107**. I<sup>2</sup>C **108** provides control inputs and monitors the status of tuner **10** and tuning PLL circuit **105**.

[0054] In operation, the front end of tuner **10** receives the entire television band through filter **101** and amplifier **102**. Following mixer **103**, the RF input is converted so that a selected channel in the RF signal appears at a first IF frequency that is selected to pass through filter **109**. The first IF frequency is then converted to a second IF frequency of 45.75 MHz at the output of mixer **110**. The frequencies of the first and second local oscillator signals will vary depending upon the specific channel in the RF signal that is desired. In the preferred embodiment, the first local oscillator frequency is selected so that mixer **103** performs an up-conversion of the RF signal. Following filter **109**, the first IF signal is then down-converted to 45.75 MHz in mixer **110**.

[0055] Following mixer **110**, the second IF signal is further processed by either digital or analog circuits. Second IF filter **113** may be constructed on the same integrated circuit substrate as the other elements of tuner circuit **10** or it may be a discrete off-chip device. When second IF filter **113** is a discrete off-chip element, then amplifiers **112** and **114** are used to provide proper impedances for filter **113** as well as to provide gain to maintain system noise performance. After amplifier **114**, the signal either remains on-chip for further processing or it can be provided to an off-chip device, such as a decoder (not shown), through buffer **115**.

[0056] If the signal is processed on-chip, then the second IF signal passes through IF AGC amplifier **116** which operates in conjunction with delayed AGC amplifier **102** to control the overall tuner gain. One output of amplifier **116** is provided to coherent oscillator (COHO) circuit **118**. COHO **118** generates two reference signals, one that is in-phase with the 45.75 MHz second IF signal and another that is 90° out-of-phase with the second IF signal. A third output from COHO **118** is provided to frequency discriminator **120** which monitors the frequency of the signal that is processed in COHO **118** and generates a tuning error signal for I<sup>2</sup>C control **108**.

[0057] AGC amplifier **116** also drives video detector **121** and audio detector **122**. Video detector **121** mixes the second IF signal with the in-phase reference signal from COHO **118**. AGC circuit **127** monitors the output of video detector **121** and adjusts the gain of amplifiers **102** and **116** in order to control the overall tuner gain. If an off-chip decoder is connected to tuner **10** through buffer **115**, then the decoder can control the signal gain by providing an input directly to AGC **127**.

[0058] The signal from video detector **121** passes through sound trap **124** which removes the audio carrier from the signal. The output of sound trap **124** drives noise clipping circuit **125** which removes large noise spikes which may be present in the video signal. Finally, a composite video signal is provided through buffer **126**.

[0059] Audio detector **122** mixes the second IF signal with the 90° out-of-phase or quadrature signal from COHO **118**.

The output signal from audio detector **122** will contain an audio carrier at 4.5 MHz and a chroma carrier at approximately 3.6 MHz. Chroma reject filter **129** is a high pass filter that removes the picture and chroma carriers from the output of audio detector **122**. The remaining audio signal is then mixed with a 5.25 MHz reference signal in mixer **130** to create a 750 KHz output. Sound filter **131** is a band pass filter that further filters the 750 KHz audio signal. FM demodulator **132** is a delay line type of demodulator which creates a standard composite audio signal from the 750 KHz FM audio signal. This audio signal is then provided as the composite audio signal through buffer **133**.

[0060] In an alternative embodiment of the present invention, a plurality of tuners **10** are placed on a single integrated substrate and a single RF input drives the plurality of tuners **10**. This allows a single integrated device to concurrently provide different television channels through the output of each tuner. This embodiment could be used to drive a "picture-in-a-picture" display or any other display format that requires multiple tuners. In another alternative embodiment, the plurality of tuners on a single substrate are coupled to independent RF signal sources and provide independent television signals.

[0061] The present invention can be used in applications other than a conventional television receiver. Tuner **10** can be embodied as part of an "add-in" board or a component of a personal computer. This allows a user to receive and view television signals on the computer's display. The user could also record or capture television programs directly to the computer's memory. The computer could then be used to replay recorded programs or to manipulate or alter selected frames or segments of the captured video and audio signal, or the computer may capture data which may have been imbedded in the video signal.

[0062] Furthermore, the present invention will be understood to not be limited to an integrated substrate. Prior art tuners require the use of a narrow-band, tunable filter to eliminate undesired channels from the receiver. The present invention is distinguished over the prior art by allowing all frequencies in a desired band to enter the front-end of tuner **10** and by removing undesired channels through filtering of the IF signal.

[0063] FIG. 2 shows multiple phase locked loop (PLL) circuits which are used to drive voltage controlled oscillators (VCOs) in order to generate the LO signals for a dual mixer conversion circuit.

[0064] Conversion circuit **20** has dual mixers **202** and **204** which receive LO signals LO1 and LO2 on lines A and B from local oscillator circuit **20**.

[0065] In a television system, signals representing individual channels are assigned to specific frequencies in a defined frequency band. For example, in the United States, television signals are generally transmitted in a band from 55 MHz to 806 MHz. The received RF signals pass through a front-end filter **200**. In the prior art, filter **200** usually was a bandpass tracking filter that allowed only a narrow range of frequencies to pass. In the preferred embodiment, filter **200** is a low pass filter that is designed to remove all frequencies above an input cutoff frequency. The input cutoff frequency is chosen to be higher than the frequencies of the channels in the television band. The output of filter

**200** then passes through amplifier **201** to adjust the signal level that is provided to mixer **202**. When conversion circuit **20** is used in a receiver circuit, amplifier **201** may be an automatic gain control (AGC) amplifier that is adjusted to maintain an overall receiver gain. Following amplifier **201**, the RE signal is provided to mixer **202** where it is mixed with a local oscillator signal LO1 from local oscillator circuit **30**. The output of mixer **202** is first intermediate frequency signal IF1. Typically, the frequency of LO1 is variable and will be selected based upon the channel in the RF signal that is being tuned. LO1 is selected so that mixing of LO1 and RF in mixer **202** generates an IF1 signal either at a specified frequency or within a narrow range of frequencies.

[**0066**] Following mixer **202**, IF filter **203** is a band pass filter that is used to remove unwanted frequencies and spurious signals from the IF1 signal. The band of frequencies that are passed by filter **203** is a matter of design choice depending upon the IF1 frequency selected in each particular conversion circuit. In the preferred embodiment, IF filter **203** is centered at 1090 MHz and has a 14 MHz pass band. This allows the selected IF1 frequency to vary within 1083-1097 MHz. Mixer **204** receives both the filtered IF1 signal from filter **203** and a second local oscillator signal (LO2) from oscillator circuit **20**. These signals are mixed to generate a second intermediate frequency (IF2) at the output of mixer **204**. In the preferred embodiment, mixer **204** is an image rejection mixer that rejects image frequencies from the IF2 signal. LO2 may be a variable or fixed frequency depending upon whether IF1 is at a fixed frequency or if it varies over a range of frequencies. In either case, the frequency of LO2 is selected to generate a fixed frequency IF2 signal. The IF2 signal is provided through amplifiers buffer **205** to additional processing circuitry (not shown) to generate either digital or analog television signals. In the preferred embodiment, the frequency of IF2 is selected to be 45.75 MHz.

[**0067**] An additional consideration when using a dual mixer conversion circuit in a television receiver is the relationship of the picture, chroma and audio carriers in an analog television signal. This is discussed in the above-referenced applications.

[**0068**] For analog television signals, it is desirable to choose a combination of LO1 and LO2 so that the relationship between the picture, chroma and audio carriers is always the same in the IF2 signal. When the IF2 signal is further processed after amplifier **205**, it may be a consideration that the analog processing circuits are able to find the chroma and audio carriers in the same place, either above or below the picture carrier, for every channel. In the preferred embodiment, LO1 and LO2 are selected so that the IF2 spectral relationship is the inverse of the RF spectral relationship. That is, the picture carrier is converted from an RF signal of 55-806 MHz to an IF2 signal at 45.75 MHz with the audio carrier 4.5 MHz below the picture carrier and the chroma carrier 3.6 MHz below the picture carrier.

[**0069**] The audio and chroma carriers are below the picture carrier frequency. This is accomplished by using the lower LO2 frequency (1041 MHz) with the higher LO1 frequency (1160.25 MHz) or using the higher LO2 frequency (1137.5 MHz) with the lower LO1 frequency (1018.5 MHz).

[**0070**] LO1 is generated in local oscillator circuit **30** (FIG. 3) by PLL**131** and LO2 is generated by PLL**232**. PLL**333** and PLL**434** provide reference inputs to PLL**232**.  $\text{I}^2\text{C}$  **320** controls local oscillator circuit **30** and causes PLL**1-431-34** to select the correct LO1 and LO2 frequencies. Local oscillator circuit **30** receives reference signals from oscillator **222** and reference frequency generator **223**. Oscillator **222** provides a 5.25 MHz output based on crystal **221**. Frequency generator **223** divides the 5.25 MHz signal from oscillator **222** to generate additional reference signals at other frequencies.

[**0071**] Local oscillator circuit **30** and PLL**1-431-34** are shown in greater detail in FIG. 3. PLL**131** provides the first local oscillator signal (LO1) to mixer **302**. PLL**232**, PLL**333** and PLL**434** cooperate to provide the second local oscillator signal (LO2) to mixer **204**. PLL**131** receives a 5.25 MHz reference signal at phase comparator **305**. The output of phase comparator **905** feeds loop amplifier **302** which, in turn, provides the input for VCO**1901**. There are two outputs from VCO**1301**. One output provides the LO1 signal to mixer **202** over line A. The other output goes into a divider network comprised of +8/+9 circuit **303** and +N circuit **304**. Divider circuits **303** and **304** divide the output of VCO**1301** down to a signal having a frequency of 5.25 MHz. This divided-down signal is compared with the 5.25 MHz reference signal in phase comparator **305** to complete the phase locked loop.

[**0072**] The output of VCO**131** is variable between 1145-1900 MHz on the high side and 572-1033 MHz on the low side. Frequencies below 572 MHz are not used in LO1 to minimize the introduction of interference frequencies into the conversion circuit. LO1 is chosen from within these ranges so that IF1 signal is within the 1090 MHz $\pm$ 7 MHz pass band of filter **303**. The 5.25 MHz reference signal creates an output stepsize of 5.25 MHz in LO1 which is utilized for coarse tuning in conversion circuit **10**. In the preferred embodiment, PLL**131** has a bandwidth on the order of 500 KHz. A wide bandwidth is preferable to get good close-in phase noise characteristics.

[**0073**] Fine tuning (for example to the exact desired channel) is accomplished by LO2 which is produced by the operation of 3 phase lock loops PLL**232**, PLL**333** and PLL**434**. PLL**434** has the same basic configuration as PLL**131**. It has reference signal of 2.625 MHz which is input to phase comparator **335**. The output of phase comparator **335** drives loop amplifier **332** which in turn drives VCO**4331**. The output of VCO**4331** has frequency range of 220-440 MHz with a 2.625 MHz stepsize and is provided to two divider circuits. One output of VCO**4331** goes to a divider network comprised of +6/+7 circuit **933** and +N circuit **334**. The effect of divider network **333** and **334** is to divide the output signal of VCO**4330** back down to 2.625 MHz. This signal is then compared with the 2.625 MHz reference signal in phase comparator **335** to complete the phase locked loop. The other output of VCO**4331** is provided to +42 circuit **330**. The output of divider **330** is a signal with a frequency range of 5.25-10.5 MHz and having a 62.5 KHz stepsize. The output of divider **330** serves as a reference signal for PLL**232**.

[**0074**] In PLL**333**, a 5.25 MHz reference signal is input to phase detector **322**. Phase detector **322** drives loop amplifier **321** which in turn drives VCO**3320**. The output of VCO**333**

is divided back down to 5.25 MHz by N circuit 323 and then fed back into phase detector 322 to complete the loop. The output of VCO333 is selectable between 1128.75 MHz and 1034.25 MHz. The selection between these two frequencies determines whether LO2 is on the high side or the low side.

[0075] In PLL232, the signal from PLL434 is received by phase comparator 314 which in turn drives loop amplifier 313. The output of loop amplifier 313 controls VCO2310. VCO2310 provides the LO2 signal for mixer 204 over line B. The LO2 signal varies between 1134.75-1140.125 MHz on the high side and 1039.875-1045.125 MHz on the low side. Another output from VCO2310 passes through buffer amplifier 311 and then drives image reject mixer 312. Mixer 312 receives its other input from PLL333. Since the signal from PLL333 is near the frequency of the LO2 signal in VCO2310, it is important that the reverse isolation between mixer 312 and VCO2310 is good to prevent the PLL333 signal from passing into the LO2 output of VCO2310. The output of mixer 312 is provided to phase comparator 314 to complete the loop in PLL232.

[0076] In the preferred embodiment, the loop bandwidths of PLL232, PLL333 and PLL434 are all wide to provide good overall close-in phase noise. PLL232 and PLL333 have bandwidths of approximately 300-500 KHz. The bandwidth of PLL434 is approximately 200-300 KHz. These bandwidths give phase noise at 100 KHz that is satisfactory for most applications.

[0077] The architecture of the frequency synthesis system provides for several benefits with respect to the overall operation of the tuner system. These benefits are in providing a lower distortion detection means, immunity to injection locking, a frequency synthesis system that allows for wide bandwidth PLLs while preserving a small step size, and providing for a choice of reference frequency that is out-of-band and that can be directly used to down-convert the audio portion of the desired channel.

[0078] A wide loop bandwidth for LO1 and LO2 is preferred because this yields good close-in phase noise characteristics for these two signals. This is important because it allows the COHO to have a narrow loop bandwidth, which yields a lower distortion video detector. For example, certain content within the video signal, such as the horizontal sync signal at approximately 15 KHz, would be partially tracked by a wide band COHO leading to distortion in the detection process. If the bandwidth of the COHO is less than 15 KHz, then the COHO would not partially track the horizontal sync signal leading to a near distortion free detection process. In the prior art, the oscillators used for conversion to IF typically do not have good close-in phase noise characteristics, requiring a COHO with wide loop bandwidth to track out this noise. It is thus typical in the prior art to employ wider bandwidth COHO's, which have the undesirable trait of partially tracking strong signals in the video signal, such as horizontal sync, leading to distortion in the detection process.

[0079] It is generally known that the immunity of a phase locked loop to injection locking is determined by the product of the quality factor, Q, of the VCO and the loop bandwidth. For the case of a VCO implemented on a single chip, it is typically difficult to realize high Qs. This conflicts with the integrated circuit implementation of a RE system with PLLs in that the other circuitry sharing the common substrate is a

source of spurs that then may be passed on to the PLLs output or lead to injection locking by the PLL. Since a high Q VCO is not feasible without external components, the benefit of a wide loop bandwidth of the PLL is more pronounced.

[0080] It is typical in the prior art to make the PLL reference frequency equal to the step size of the frequency synthesizer system. It is further typical of the prior art to employ a single loop frequency synthesizer to create the first LO in tuners. For example, if the step size of the system was 62.5 KHz, then the reference frequency to the single loop PLL would also be 62.5 KHz. It is highly desirable to suppress harmonics and spurs of the reference that are in band to a level below the noise floor of the VCO, requiring the loop bandwidth of the PLL to be less than the reference frequency. In the case where the reference is the step size, the loop bandwidth is rather narrow. Consequently, is a clear advantage of the frequency synthesizer described herein to provide both a small step size as well as a wide bandwidth for LO1 and LO2 providing for enhanced immunity to spurs as well as providing for a narrow bandwidth COHO.

[0081] A further advantage of the frequency synthesis system is that it can use a reference that is above the baseband frequencies. An example of such a frequency is 5.25 MHz. It should be noted that this 5.25 MHz reference is above the baseband signal of the system, thus avoiding in-band noise produced by the reference and its harmonics. A further advantage of this choice of reference is that it can be used directly by the audio subsystem to down convert the frequency modulated audio signal to a lower frequency usable by the sound filter and FM demodulator in the audio subsystem. This eliminates the need for a PLL to create this frequency.

[0082] Although the present invention and its advantages have been described in detail, it should be understood that various changes, substitutions and alterations can be made herein without departing from the spirit and scope of the invention as defined by the appended claims. Moreover, the scope of the present application is not intended to be limited to the particular embodiments of the process, machine, manufacture, composition of matter, means, methods and steps described in the specification. As one of ordinary skill in the art will readily appreciate from the disclosure of the present invention, processes, machines, manufacture, compositions of matter, means, methods, or steps, presently existing or later to be developed that perform substantially the same function or achieve substantially the same result as the corresponding embodiments described herein may be utilized according to the present invention. Accordingly, the appended claims are intended to include within their scope such processes, machines, manufacture, compositions of matter, means, methods, or steps.

1.-71. (canceled)

72. A television receiver comprising:

- a receiver input coupled to an RE signal source;
- a first reference signal having a first operating frequency;
- a first mixer having a first input coupled to said receiver input and a second input coupled to said first reference signal;

a bond-wire parallel Inductive Capacitive (LC) filter coupled to an output of said first mixer; the bond-wire parallel LC filter passing more than one channel and performing partial image rejection as well as limiting overall signal power levels to be processed by subsequent circuitry, wherein the more than one channel passed by the bond-wire parallel LC filter is attenuated;

a first and a second phase locked loop providing reference inputs for a third phase locked loop;

a second reference signal produced by said third phase locked loop having a second operating frequency; and

an image rejection mixer having a first input coupled to an output of said bond-wire parallel LC filter and a second input coupled to said third phase locked loop to receive said second reference signal.

73. The television receiver of claim 72 wherein said first mixer, said bond-wire parallel LC filter, and said image rejection mixer comprise a differential mixer chain.

74. The television receiver of claim 72 wherein said first mixer and said image rejection mixer are constructed on a same integrated circuit substrate.

75. The television receiver of claim 72 wherein said bond-wire parallel LC filter is external to an integrated circuit on which said first mixer is located.

76. A television receiver comprising:

- a receiver input for receiving an RF signal;
- an input filter coupled to said receiver input and operating to remove all frequency components in said RF signal above an input cutoff frequency to produce a filtered RF signal;
- a first reference signal having a first operating frequency;
- a first mixer having a first input coupled to an output of said input filter and a second input coupled to said first reference signal;
- a digital interface providing control with respect to said first mixer; wherein said digital interface comprises an inter-integrated circuit interface;
- a second reference signal having a second operating frequency; and

a second mixer having a first input coupled to an output of said first mixer and a second input coupled to said second reference signal; and

a filter between said first and second mixers;

wherein said second mixer is an image rejection mixer, wherein said first mixer and said second mixer are physically located in the same integrated circuit substrate.

77. The television receiver of claim 76 wherein said first mixer, said filter and said second mixer comprise a differential mixer chain.

78. The television receiver of claim 76 wherein said first and second mixers are constructed on a same integrated circuit substrate.

79. The television receiver of claim 72 wherein said first bandpass filter is external to an integrated circuit on which said first mixer is located.

80. The television receiver of claim 76 wherein said filter comprises:

a bond-wire parallel Inductive Capacitive (LC) filter.

81. A method of processing a received RF signal, the method comprising the steps of:

- attenuating frequency components of said RF signal above a cut-off frequency to create a filtered RF signal;
- mixing the RF signal with a first reference signal having a first operating frequency to thereby produce a first IF signal;
- controlling a frequency of said first operating frequency for said mixing the filtered RF signal using a digital interface;
- filtering the first IF signal in a bandpass filter to produce an output passband signal having a plurality of channels; and
- mixing the output passband signal with a second reference signal having a second operating frequency to thereby produce a second IF signal, wherein said mixing the filtered RE signal and said mixing the output passband signal are performed in a single integrated circuit.

\* \* \* \* \*